Reporting for Contact Center Setup and Operations Guide

BCM50 3.0
Contact Center

Document Number: NN40040-303
Document Status: Standard
Document Version: 01.01
Date: August 2007

NORTEL

Copyright © 2006-2007 Nortel Networks, All Rights Reserved

The information in this document is subject to change without notice. The statements, configurations, technical data, and recommendations in this document are believed to be accurate and reliable, but are presented without express or implied warranty. Users must take full responsibility for their applications of any products specified in this document. The information in this document is proprietary to Nortel Networks.

Trademarks

Nortel, the Nortel logo, and the Globemark are trademarks of Nortel Networks.

Microsoft, MS, MS-DOS, Windows, and Windows NT are registered trademarks of Microsoft Corporation.

Java is a trademark of Sun Microsystems Incorporated.

All other trademarks and registered trademarks are the property of their respective owners.

Table of Contents

List of Figures 6

List of Tables 9

How to Use this Guide 11

Introduction 11
How this guide is organized 11
How to get Help 12
Getting Help from the Nortel Web site 12
Getting Help over the phone from a Nortel Solutions Center 12
Getting Help through a Nortel distributor or reseller 12

Introduction 13

Web-Based User Interface 13
Language Support 13
Administrators and Users 14
Assigned Skillsets 14
SQL Historical Database 14
System Software 15
PC Requirements 15
Recommended Minimum PC Specification for BCM50 3.0 15
Operating System Compatibility 16

Installation 17

Introduction 17
Upgrading to Reporting for Contact Center 17
Uninstalling Reporting for Contact Center 17
Upgrading a Previous Version of Reporting for Contact Center 18
Deleting Temporary Internet Files 18
Installation prerequisites 20
Installing Microsoft Internet Information Services 21
Port Numbers used by Nortel Reporting for Contact Center 26
Settings required for Windows Vista with IIS 7.0 26
Installing Nortel Reporting for Contact Center software 29
TCP/IP Protocol 29
Checking Installation of the Windows Networking Component 29
Installing Nortel Reporting for Contact Center for a Business Communications Manager Installation 30
Install Verification Utility 46
Print Caller Service 49
To quit the PCS 56

Administration 57

Logging In 57
Changing Default Password 58
Contact Center Connection 60
Administration Menu 64
System Administration 65
System Admin Settings 66
User Admin 67
Skillset Assignment 72
Maintenance 76
System Status 76
Logging 78
Company Details 79
Reporting 80

Using Reporting for Contact Center 81

Logging On 81
Real Time 84
Using the Real Time Options 84
Real Time Call Summary 85
Real Time Agent Summary 88
Real Time Call Detail 90
Real Time Agent Detail 92
Agent Alarms 98
Wallboard Setup 102
Message Formats 102
Parameter Messages 102
Scrolling Messages 103
Summary Messages 104
Using the Wallboard Options 105
Wallboard Assignment 106
Messages 112
Alarms 117
Schedules 123
Instant Messages 128
Time Bins Setup 131
Answer Time Bins 131
Abandon Time Bins 131
Schedules 135
Daily Schedules 136
Skillset List Selection Methods 141
Adding Selections to the Favorites List 141
Saving your Daily Schedule 143
Weekly Schedules 146
Weekly Schedules Skillsets 149
Saving Your Weekly Schedule 150
Monthly Schedules 153
Monthly Schedule Skillsets 157
Saving your Monthly Schedule 158

Reports 161

Reports Introduction 161
General 161

Reports Explained 161
Using the Reports 161
Generating reports 163
View a report on screen 164
Send a report directly to the printer 164
Cancel reports to be printed 167
Selecting Skillsets 167
Selecting Agents 168
Selecting Activity Codes 170
Get Latest Contact Center Data item 171

Glossary 173

References 177

Index 178

List of Figures

Figure 1: Internet Properties dialog box 19
Figure 2: Delete Files dialog box 19
Figure 3: Add or Remove Programs 21
Figure 4: Windows Components Wizard 22
Figure 5: Windows Components Wizard Installation 23
Figure 6: Windows Components Wizard Installation Completed 24
Figure 7 : Internet Information Services test page 25
Figure 8: Windows features option in Programs and Features window 27
Figure 9: Turn Windows features on or off dialog box 28
Figure 10: Download the Reporting for Contact Center Software 31
Figure 11: InstallShield Initialization dialog box 32
Figure 12: RCC Compatibility Check dialog box 32
Figure 13: RCC Compatibility Check – creating backup files 33
Figure 14: RCC Compatibility Check – insufficient memory error message 33
Figure 15: Choose Setup Language dialog box 34
Figure 16: InstallShield Requirements dialog box 34
Figure 17: MDAC 2.8 End User License Agreement dialog box 35
Figure 18: MDAC installation dialog box 36
Figure 19: Microsoft Data Access Components system restart dialog box 37
Figure 20: InstallShield RCC requirements for SQL Server and Report Viewer dialog box 38
Figure 21: InstallShield RCC requirements dialog box 39
Figure 22: InstallShield Wizard RCC Welcome dialog box 40
Figure 23: License Agreement dialog box 41
Figure 24: Exit Setup warning message box 41
Figure 25 : Choose Destination Location dialog box 42
Figure 26: Setup Status dialog box 43
Figure 27: Java installation dialog box 43
Figure 28: Installation Complete dialog box 44
Figure 29: RCC Monitor splash screen 45
Figure 30: RCC Database Installer Utility 45
Figure 31: RCC Install Verification Utility 46
Figure 32: BCM Connection Data dialog box 47
Figure 33: RCC Install Verification Utility verifying BCM connection 48
Figure 34: Save BCM connection settings message box 48
Figure 35: RCC Install Verification Utility verification success 49
Figure 36: Print Caller Service information balloon 50
Figure 37: Print Caller Service menu 50
Figure 38: RCC Print Caller Service window 50
Figure 39: RCC Print Caller Service window – PCS stopped 51
Figure 40: Print Caller Service warning balloon 51
Figure 41: Print Caller Service menu – Start function 51
Figure 42: RCC Print Caller Service window - Windows service mode 52
Figure 43: RCC Print Caller Service mode change message box 52
Figure 44: Set Service Login dialog box 53
Figure 45: RCC Print Caller Services settings changed message box 53
Figure 46: Print Caller Service menu for Windows service 54
Figure 47: RCC Print Caller Service mode change to background application message box 54
Figure 48: RCC Print Caller Service window – Windows service mode 55
Figure 49: RCC Print Caller Service window – PCS stopped as a Windows service 55
Figure 50: Print Caller Service shut down warning message 56
Figure 51: Login page 58
Figure 52: Change Password page 59

Figure 53: Contact Center Connection page 60
Figure 54: Download Contact Center Data options 62
Figure 55: Download Status window 62
Figure 56: Administration Menu page 64
Figure 57: System Administration Menu page 65
Figure 58: System Administrator details page 66
Figure 59: User Admin page 67
Figure 60: Add User page 68
Figure 61: Details for new User Mary Smith 70
Figure 62: Edit User page 71
Figure 63: Skillset Assignment page 73
Figure 64: Assigned Skillsets page 74
Figure 65: Skillsets Assigned to User Mary Smith 75
Figure 66: Maintenance Menu page 76
Figure 67: System Status page 77
Figure 68: Logging Menu page 78
Figure 69: Company Details page 79
Figure 70: Main Menu page 80
Figure 71: Change Password page 82
Figure 72: User Main Menu page 83
Figure 73: Real Time page 84
Figure 74: Call Summary Real Time screens 85
Figure 75: Agent Summary Real Time screen 88
Figure 76: Real Time Call Detail Screen 90
Figure 77: Agent Detail Real Time 92
Figure 78: Available state 93
Figure 79: Break Time state 93
Figure 80: All Calls Held state 93
Figure 81: Incoming (PSTN) state 94
Figure 82: Incoming Non-CC state 94
Figure 83: Intercom state 94
Figure 84: Multimedia state 95
Figure 85: Monitoring state 95
Figure 86: Not Available state 96
Figure 87: Not Ready state 96
Figure 88: Outgoing Call state 96
Figure 89: Ringing state 96
Figure 90: Agent Alarms menu page 98
Figure 91: Agent Alarms Setup page 99
Figure 92: Agent Alarms Values page 100
Figure 93: Wallboard Menu page 105
Figure 94: Wallboard Assignment page 106
Figure 95: Add Wallboard page 107
Figure 96: Wallboard Setup page with a wallboard listed 109
Figure 97: Edit Wallboard page 110
Figure 98: Edit Parameters page 111
Figure 99: Assigned Messages page 113
Figure 100: Add Message page 114
Figure 101: Add Message page – example text 115
Figure 102: Assigned Messages list – example messages 116
Figure 103: Assigned Alarms page 117
Figure 104: Add Alarm page 118
Figure 105: Example Settings for a Multi Alarm Period Alarm 121
Figure 106: Assigned Alarms page with an alarm configured 123
Figure 107: Assigned Schedules page 124
Figure 108: Add Schedule page 125

Figure 109: Assigned Schedules page with schedule added....126
Figure 110: Edit Schedule page....127
Figure 111: Instant Messages page....128
Figure 112: Composing an Instant Message....129
Figure 113: Time Bin Setup Skillset selection page....132
Figure 114: Time Bins page....133
Figure 115: Reports and Schedules page....136
Figure 116: Your Daily Schedules page....137
Figure 117: Add Daily Schedule page....138
Figure 118: Add Daily Schedule page – example settings....139
Figure 119: Daily Schedule Skillsets page....140
Figure 120: Save Favorites page....142
Figure 121: Your Daily Schedules with a Schedule in the List....143
Figure 122: Edit Daily Schedules page....145
Figure 123: Your Weekly Schedules page....146
Figure 124: Add Weekly Schedule page....147
Figure 125: Calendar for September 2003....148
Figure 126: Add Weekly Schedule page – example schedule....149
Figure 127: Weekly Schedules - Skillsets....150
Figure 128: Your Weekly Schedule page with a Print Schedule in the list....151
Figure 129: Edit Weekly Schedule page....152
Figure 130: Your Monthly Schedules page....154
Figure 131: Add Monthly Schedule Page....155
Figure 132: Add Monthly Schedule page with example schedule....156
Figure 133: Monthly Schedule - Skillsets page....157
Figure 134: Your Monthly Schedules page with a Print Schedule in the list....158
Figure 135: Edit Monthly Schedule page....160
Figure 136: Reports and Schedules page....162
Figure 137: Selecting a Date Range....164
Figure 138: Print Status page....166
Figure 139: Select Skillsets page....168
Figure 140: Select Agents or Skillsets page....169
Figure 141: Select Activity Codes page....170
Figure 142: Get Latest Contact Center Data....171

List of Tables

Table 1: Administrator and User Permissions 69

How to Use this Guide 1

Introduction

This guide is designed to allow an Administrator or User to set up and operate Nortel Reporting for Contact Center.

How this guide is organized

The *Reporting for Contact Center Setup and Operations Guide* is organized as follows:

How to Use this Document	Provides a brief overview identifying the organization of this guide. Details also given on how to get help from Nortel.
Introduction	Provides an overview of the conceptual organization of the Nortel Reporting for Contact Center product.
Installation	Describes the minimum specification for the Personal Computer (PC) required that hosts the Nortel Reporting for Contact Center software. It also describes how to install Nortel Reporting for Contact Center.
Administration	Describes the required administration duties and configuration to ensure that Nortel Reporting for Contact Center operates correctly.
Using Reporting for Contact Center	Describes the use and configuration of Nortel Reporting for Contact Center from a user's perspective.
Reports	Describes the reports that are available within Nortel Reporting for Contact Center.
Glossary	Describes the terms used in this guide.
References	Lists documents referenced in this guide.
Index	Provides a cross-reference of topics in this guide.

How to get Help

This section explains how to get help for Nortel products and services.

Getting Help from the Nortel Web site

The best source of support for Nortel products is the Nortel Support Web site:

http://www.nortel.com/support

This site enables customers to:

- Download software and related tools
- Download technical documents, release notes, and product bulletins
- Sign up for automatic notification of new software and documentation
- Search the Support Web site and Nortel Knowledge Base
- Open and manage technical support cases

Getting Help over the phone from a Nortel Solutions Center

If you have a Nortel support contract and cannot find the information you require on the Nortel Support Web site, you can get help over the phone from a Nortel Solutions Center.

In North America, call 1-800-4NORTEL (1-800-466-7835).

Outside North America, go to the following Web site and look up the phone number that applies to your region:

http://www.nortel.com/callus

When you speak to the phone agent, you can reference an Express Routing Code (ERC) to route your call more quickly to the appropriate support specialist. To locate the ERC for your product or service, go to:

http://www.nortel.com/erc

Getting Help through a Nortel distributor or reseller

If you purchased a service contract for your Nortel product from a distributor or authorized reseller, you can contact the technical support staff for that distributor or reseller.

Introduction 2

Nortel Reporting for Contact Center is a browser-based Real Time information and Historical Reporting tool for the Nortel Contact Center.

Nortel Reporting for Contact Center provides:

- Real Time windows showing current Contact Center activity for calls and for agents
- Real Time information through hardware and software IP-enabled wallboards
- A comprehensive Historical Reporting package

Note: In this document, the phrase *the Contact Center platform* is used to refer to either the Business Communications Manager or the CallPilot hardware, and the phrase *the Contact Center* is used to refer to the Contact Center application running on that platform. The platforms are referenced specifically by name in areas of this document such as those that describe the information concerning the configuration of the Contact Center Connection page (see Contact Center Connection on page 60).

Web-Based User Interface

All the administrative and user interactions with Nortel Reporting for Contact Center are conducted through a series of Web pages that are accessed through Internet Explorer browser sessions.

The Web pages are hosted on a designated PC, referred to as the Web Host PC, on which the Nortel Reporting for Contact Center software is installed. The Web Host PC communicates directly with the Contact Center to retrieve Real Time updates (for the Real Time screens and wallboards) and Historical information (for the reports).

Other PCs that have network access to the Web Host PC can access these Web pages. Multiple users can, therefore, use Nortel Reporting for Contact Center without having any software other than Internet Explorer installed on their PCs. (The Java Runtime Environment, if required, and the ActiveX Report Viewer are automatically downloaded to the client the first time they are required.)

Language Support

Each Administrator or User of Nortel Reporting for Contact Center can specify to view their Web user interface pages in one of the following 13 languages: North American English, United Kingdom English, Canadian French, Latin American Spanish, Brazilian Portuguese, Spanish, Dutch, French, German, Italian, Norwegian, Danish, and Swedish.

Each Administrator or User can also view individual wallboards in any of these languages.

Administrators and Users

The two types of Nortel Reporting for Contact Center users are Administrators and Users.

In addition to having access to all the features of Nortel Reporting for Contact Center, Administrators can specify and change fundamental configuration settings within Nortel Reporting for Contact Center.

For security purposes and to maintain system stability, only Users with Administrator capabilities can change the fundamental configuration settings. User interactions with Nortel Reporting for Contact Center are limited to using the features that it provides.

While Users cannot modify the core setup of Nortel Reporting for Contact Center, they can specify and change some personal preferences. Users can also configure any aspects of Nortel Reporting for Contact Center that affect only themselves.

Administrators and Users view different menus when they log in.

Assigned Skillsets

Administrators create Users by providing details, such as User Name and language, to Nortel Reporting for Contact Center. The Administrator must then assign Skillsets to Users.

The process of assigning Skillsets defines the Skillsets that each User can view in the Real Time screens and for which the User can request Historical Reports. Skillsets can be assigned to more than one User.

Users can choose to view the Real Time screens or Historical Reports for any of the Skillsets assigned to them, any combination of the allocated Skillsets, or all the assigned Skillsets.

Users, including the Administrator, can save frequently used Selections of Skillsets as Favorites and assign names to the Favorites. The User can then, with a single mouse click, quickly locate a Skillset selection. Favorites are unique to each User. Users can create, modify, or delete their Favorites without affecting the Favorites of other Users.

SQL Historical Database

Historical Report information is stored in a standard Microsoft SQL Server 2005 Express database. If Users have reporting requirements that are not available through Nortel Reporting for Contact Center, they can analyze the data using third-party reporting packages.

System Software

The software that sends data to Nortel Reporting for Contact Center is integral to the Nortel Contact Center.

Nortel Reporting for Contact Center software on the Web Host PC communicates directly with the Contact Center to request Contact Center Historical Report statistical data and Real Time data.

Users on other PCs can access the Real Time and Historical Report data by pointing their Internet browsers to the Nortel Reporting for Contact Center Web pages on the Web Host PC. Only the Web Host PC needs to communicate with the Contact Center.

Note: One PC on your network should be designated as the Web Host PC. Install the Nortel Reporting for Contact Center application software onto this designated PC only.

If there are multiple Contact Centers on the network, multiple Web Host PCs are required. A single Web Host PC, with a particular version of Reporting for Contact Center installed, can only connect to a single Contact Center.

All other network PCs from which Users access the Real Time screens, Historical Reports, or the Nortel Reporting for Contact Center user interface must be equipped with Internet Explorer. No other software is required on these PCs.

PC Requirements

The minimum recommended requirements for the PC designated as the Nortel Reporting for Contact Center Web Host PC for BCM50 3.0 are as follows:

Recommended Minimum PC Specification for BCM50 3.0

IBM™ Compatible PC

Microprocessor
Intel® Pentium™ IV (or equivalent) minimum

Microprocessor Speed
1.7 GHz minimum

Memory
512 MB minimum

Network Interface Card
TCP/IP protocol
SVGA display

Mouse (or other Windows®-compatible pointing device)
Microsoft Internet Explorer version 6.0 Service Pack (SP) 1, or later

Web Server
Nortel Reporting for Contact Center has been verified with Microsoft Internet Information Services 5.0, or later.

Nortel Reporting for Contact Center is supported on a single PC only and is not intended to run on Cluster Servers like those supported by Windows 2003 Enterprise.

Hard Disk Space Required
For installation and operation of application on Web Server: 1.4 GB
Recommended storage space for Historical Data: 4 GB

Operating System Compatibility

Nortel Reporting for Contact Center is verified for correct operation on the following operating systems:

Operating System	Version
Windows 2000	5.00.2195, SP4
Windows XP	Professional, Version 2002, SP2
Windows Server 2003	Standard Edition, SP1
Windows Vista	Business or Ultimate Edition

Installation 3

Introduction

This chapter describes the installation prerequisites and the procedure for installing the Nortel Reporting for Contact Center software on the Windows Personal Computer that is designated as the Web Host PC. The Web Host PC communicates with the Nortel Contact Center. The Web Host PC also stores the Contact Center statistical database and the Nortel Reporting for Contact Center user interface, which is configured as a Web site.

Users of other network PCs can use Internet Explorer to access the Nortel Reporting for Contact Center Web site on the Web Host PC. From the Web site, Users can access the software features and can obtain Real Time displays and Reports.

Upgrading to Reporting for Contact Center

This section describes the installation of Nortel Reporting for Contact Center from Nortel Networks Call Center Reporting on a Web Host PC.

If you are upgrading from Call Center Reporting 2.5, 3.0, or 3.5, refer to the *Upgrading from Call Center Reporting to Reporting for Contact Center* (NN40010-400) document.

If you are upgrading from a previous version of Nortel Reporting for Contact Center to a newer version of Nortel Reporting for Contact Center, refer to the following section, Upgrading a Previous Version of Reporting for Contact Center.

Uninstalling Reporting for Contact Center

Perform the following steps to uninstall Nortel Reporting for Contact Center:

1. From the **Start** menu select **Settings > Control Panel** to open the Control Panel window.
2. Double-click **Add or Remove Programs**.
3. From the list of programs select **Reporting for Contact Center**.
4. Click the **Change/Remove** button to open InstallShield Wizard.
5. Select the **Remove** option and click **Next**.
6. Follow the on-screen instructions of InstallShield Wizard to complete the un-installation.

Note: The Reporting for Contact Center directory will be left behind along with folders and files required for log information for any saved Log files from activity in the uninstalled version of Reporting for Contact Center.

To remove these files, the user must manually delete them using Windows Explorer.

Upgrading a Previous Version of Reporting for Contact Center

To upgrade a previous version of Nortel Reporting for Contact Center, perform the following steps:

1. Uninstall the current version of Nortel Reporting for Contact Center from the Web Host PC, refer to Uninstalling Reporting for Contact Center on page 17.

2. Install the latest version of Nortel Reporting for Contact Center from the location that this resides and double-click on the Reporting for Contact Center .exe file.

3. **InstallShield Wizard** will open up. Follow the on-screen instructions to be guided through the installation process.

   Note: You **DO NOT** need to uninstall Microsoft SQL Server 2005, Microsoft .NET Framework 2.0, or Java SE Runtime Environment 6.

If required the Nortel Reporting for Contact Center databases are modified during the installation. There is no loss of statistical data, but new data, tables, columns, and/or indexes may be added to them.

Deleting Temporary Internet Files

To prevent Internet Explorer from caching old versions of the Nortel Reporting for Contact Center Web pages, delete the temporary Internet files on your computer. Follow these steps to delete temporary Internet files.

1. Click **Start**, then right-click the **Internet Explorer** icon, and select **Internet Properties**. See Figure 1: Internet Properties dialog box.



Figure 1: Internet Properties dialog box

Note: If you do not see the dialog box shown in Figure 1: Internet Properties dialog box, you have clicked a shortcut to Internet Explorer. You **must** click the Internet Explorer icon in the Start menu.

2. When you see the window shown in Figure 1: Internet Properties dialog box, click **Delete Files**. The **Delete Files** dialog box shown in Figure 2: Delete Files dialog box appears.


Delete Files
Delete all files in the Temporary Internet Files
You can also delete all your offline content stored locally.
Delete all offline content
OK
Cancel

Figure 2: Delete Files dialog box

3. Select **Delete all offline content**, and then click **OK**.

4. Click **OK** to close the **Internet Properties** window.

Proceed with the installation of Nortel Reporting for Contact Center, as described in Installation prerequisites.

It may also be necessary to clear your Java Cache when upgrading Nortel Reporting for Contact Center. This is not strictly necessary but should any problems be seen after the upgrade consult the *Reporting for Contact Center Troubleshooting and Maintenance Guide* (NN40020-403).

Installation prerequisites

Before you install Nortel Reporting for Contact Center software, you must:

- Be familiar with the Contact Center and the Windows™ operating system used by your Web Host PC.
- Ensure that the Contact Center is installed and configured.
- Ensure that the Contact Center platform is connected to, and is operational on, the network to which the Nortel Reporting for Contact Center Web Host PC is connected.
- Ensure that the full suite of Microsoft Internet Information Services is installed and operational on the Web Host PC, and that the Default Web Site is enabled. To install Microsoft Internet Information Services, refer to Installing Microsoft Internet Information Services.
- For BCM50 3.0, as the Nortel Reporting for Contact Center installation includes Microsoft .NET Framework 2.0, ensure Microsoft .NET Framework 1.2 or later, are uninstalled from the Web Host PC before installing Nortel Reporting for Contact Center. This is because Microsoft .NET Framework 1.2, or later, are not compatible with SQL Server 2005 Express which is included in the BCM50 3.0 Nortel Reporting for Contact Center installation.

  Note: Microsoft .NET Framework versions 1.0, 1.1 and 2.0 do not have to be uninstalled.

  To check and uninstall the incompatible versions of .NET Framework installed on the Web Host PC, perform the following:

  1. From the **Start** menu, select **Settings > Control Panel**.
  2. Double-click on **Add or Remove Programs**.
  3. View the list of programs installed on the PC. If **Microsoft .NET Framework 1.2**, or a later version, is listed, click on the **Remove** button.

4. Follow the InstallShield Wizard instructions to uninstall the program.

Installing Microsoft Internet Information Services

You can install Microsoft Internet Information Services through the Add or Remove Programs dialog box, using the Add/Remove Windows Components icon. See Figure 3: Add or Remove Programs.



Figure 3: Add or Remove Programs

Follow these steps to install Microsoft Internet Information Services:

1. On the Windows taskbar, select **Start** > **Settings** and then click **Control Panel**. The **Control Panel** window appears.

2. Double-click the **Add or Remove Programs** icon. The Add or Remove Programs dialog box appears.

3. Click **Add/Remove Windows Components**. The Windows Components Wizard appears, as shown in Figure 4: Windows Components Wizard.


Windows Components Wizard
Windows Components
You can add or remove components of Windows XP.
To add or remove a component, click the checkbox. A shaded box means that only part of the component will be installed. To see what's included in a component, click Details.
Components:
Indexing Service 0.0 MB
Internet Explorer 0.0 MB
Internet Information Services (IIS) 13.5 MB
Management and Monitoring Tools 2.0 MB
Message Queuing 0.0 MB
Description: Includes Web and FTP support, along with support for FrontPage, transactions, Active Server Pages, and database connections.
Total disk space required: 22.1 MB
Space available on disk: 26583.5 MB
Details...
< Back
Next >
Cancel

Figure 4: Windows Components Wizard

4. Select **Internet Information Services (IIS)**. The background of the check box turns grey, indicating that only the basic components of Internet Information Services will be installed. You do not need to install any additional components for Reporting for Contact Center to work properly. Installing additional components is optional, and additional components do not affect the operation of Reporting for Contact Center.

5. Click **Next**. The Configuring Components dialog box appears. See Figure 5: Windows Components Wizard Installation.


Windows Components Wizard
Configuring Components
Setup is making the configuration changes you requested.
Please wait while Setup configures the components. This may take several minutes, depending on the components selected.
Status: Configuring Internet Information Services (IIS)...
< Back
Next >
Cancel

Figure 5: Windows Components Wizard Installation

Windows now installs your Internet Information Services component.

You may be prompted for additional installation files (typically from a CD). If you are prompted for additional files, insert the Windows operating system installation disk that was used to install the Windows operating system of the Web Host PC, and click **OK**. If you do not use the same disk, you cannot complete the installation.

6. When Internet Information Services installation is complete, you receive a message that confirms successful completion. See Figure 6: Windows Components Wizard Installation Completed.

Windows Components Wizard
Completing the Windows Components Wizard
You have successfully completed the Windows Components Wizard.
To close this wizard, click Finish.
< Back
Finish

Figure 6: Windows Components Wizard Installation Completed

Click **Finish** to return to the Add or Remove Programs dialog box. You can close the Add or Remove Programs dialog box and the Control Panel window.

7. To test that the Internet Information Service is properly installed, open Internet Explorer and in the Address bar enter:
   http://localhost/

   If the installation is successful, a window similar to the window in Figure 7 : Internet Information Services test page appears.


Welcome to Windows XP Server Internet Services - Microsoft Internet Explorer
File Edit View Favorites Tools Help
Back Search Favorites
Address http://localhost/localstart.asp
Go Links
Microsoft Windows xp Professional
Your Web service is now running.
You do not currently have a default Web page established for your users. Any users attempting to connect to your Web site from another machine are currently receiving an Under Construction page. Your Web server lists the following files as possible default Web pages: default.htm,default.asp,index.htm,iisstart.asp,default.aspx. Currently, only iisstart.asp exists.
To add documents to your default Web site, save files in c:\inetpub\wwwroot\.
Welcome to IIS 5.1
Internet Information Services (IIS) 5.1 for Microsoft Windows XP Professional brings the power of Web computing to Windows. With IIS, you can easily share files and printers, or you can create applications to securely publish information on the Web to improve the way your organization shares information. IIS is a secure platform for building and deploying e-commerce solutions and mission-critical applications to the Web.
Using Windows XP Professional with IIS installed, provides a personal and development operating system that
Integrated Management
You can manage IIS through the Windows XP Computer Management console or by using scripting. Using the console, you can also share the contents of your sites and servers that are managed with Internet Information Services to other people via the Web. Accessing the IIS snap-in from the console, you can configure the most common IIS settings and properties. After site and application development, these settings and properties can be used in a production environment running more powerful versions of Windows servers.
Done
Local intranet

Figure 7 : Internet Information Services test page

This window also contains useful information regarding your Internet Information Services. You can see the current version number and additional information about where to find extended help for Internet Information Services.

If you see a Page Cannot be Displayed screen, re-install the Internet Information Services and reboot the Web Host PC.

To ensure correct operation of Nortel Reporting for Contact Center, observe the following points:

- The IP address setting for the default Web site should be **All Unassigned**, or the IP address setting for the default Web site should be 127.0.0.1 and the host header should be localhost.
- The port should be set to 80.
- Ports 3500, 6010, and 6011 must not be blocked by local firewalls.

Port Numbers used by Nortel Reporting for Contact Center

The list below gives all the port numbers used by Nortel Reporting for Contact Center on the Web Host PC:

- Port 80 – this is the standard port used by the Web Server (the Web Host PC) for Internet Information Services.
- Port 8088 – used for the Reporting Server in the Business Communications Manager.
- Port 3500 – used by *ip***View** SoftBoard to listen for incoming data and to echo to other wallboards. For more information on the *ip***View** SoftBoard, refer to *ipView Software Wallboard Setup and Operation Guide* (NN40010-500).
- Port 6010 – used for the Reporting for Contact Center Real Time (RCCRT) Server.
- Port 6011 – used for the Reporting for Contact Center Reporting (RCCRPT) Server.

Note: Nortel recommends that you ensure your Web Host PC Internet Information Services installation is as secure as possible. Generally, a secure installation involves loading security patches and/or service packs for Internet Information Services and for the operating system of the Web Host PC. These patches and service packs are available free of charge by Microsoft. Contact your network administrator for further advice.

You are now ready to install the Nortel Reporting for Contact Center software from the Contact Center platform. See Installing Nortel Reporting for Contact Center software.

Settings required for Windows Vista with IIS 7.0

In order to install Reporting for Contact Center on a Windows Vista operating system some Windows Internet Information Services (IIS) features have to be turned on.

Perform the following steps to enable Windows features on a Windows Vista operating system using IIS 7.0 that are required for a Reporting for Contact Center installation:

1. Click on the Start menu and select **Program Files > Control Panel**.

2. Double-click on **Programs and Features**.
3. From the left panel click on the **Turn Windows features on or off** option. See Figure 8: Windows features option in Programs and Features window.



Figure 8: Windows features option in Programs and Features window

The Windows Features window will open.

4. Expand the following:
    - **Internet Information Services > Web Management Tools > IIS 6 Management Compatibility**. Select the following check boxes:
        - IIS 6 WMI Compatibility
        - IIS Metabase and IIS 6 configuration compatibility
    - **Internet Information Services > World Wide Web Services > Application Development Features**. See Figure 9: Turn Windows features on or off dialog box. Select the following check boxes:
        - ASP

- ASP.Net
- ISAPI Extensions
- ISAPI Filters

- **Internet Information Services > World Wide Web Services > Common Http Features**. Select the following check boxes:
  - Default Document
  - HTTP Redirection
  - Directory Browsing
  - Static Content

- **Internet Information Services > World Wide Web Services > Security**. Select the following check boxes:
  - Request Filtering
  - Windows Authentication



Figure 9: Turn Windows features on or off dialog box

5. Click **OK** on the Windows Feature dialog box.

   IIS 7.0 will now allow Reporting for Contact Center to be installed on the Windows Vista operating system.

Installing Nortel Reporting for Contact Center software

Note: You **must** have Administrator rights for the installation to be successful. If you do not have Administrator rights for the PC on which you wish to install Nortel Reporting for Contact Center, the installation is halted and you are requested to log out and log back in with Administrator rights.

By default, Nortel Reporting for Contact Center software creates a folder in the location \Program Files\Nortel\Nortel Reporting for Contact Center on the installation drive of the Web Host PC. This folder contains the application files used by Nortel Reporting for Contact Center. The folder also contains the Nortel Reporting for Contact Center configuration and statistical database.

Note: Before Nortel Reporting for Contact Center will operate correctly, you must enable the Contact Center Reporting Software Keycode. For Software Keycode information, refer to the Software Keycode Installation Guide.

TCP/IP Protocol

The Contact Center platform and Nortel Reporting for Contact Center use the industry standard TCP/IP protocol for communication between the Contact Center and the Nortel Reporting for Contact Center Web Host PC. The Windows Network component is required for the Nortel Reporting for Contact Center Web Host PC. Refer to Checking Installation of the Windows Networking Component.

The Nortel Reporting for Contact Center installation process does not install the Windows Network component. For instructions about installing the Windows Networking component, refer to your network or Windows documentation.

Checking Installation of the Windows Networking Component

Follow the steps in this section to check that the Windows Networking component is set up properly on the PC that will operate as the Web Host PC.

Note: If your company has a network administrator, check with your administrator before changing any network configuration parameters.

1. Start the Windows system on the PC where the Nortel Reporting for Contact Center application is installed.

2. On the Windows taskbar, select **Start** > **Settings** and then click **Control Panel**. The Control Panel window appears.

   If you are using the Windows 2000 operating system, double-click **Networking and Dial-up Connections**. The Networking and Dial-up Connections window appears.

   If you are using the Windows XP operating system, select **Start > Connect to** and then click **Show All Connections**. The Networking Connections window appears.

3. Double-click the **Network** icon. The Network window appears with the Configuration tab displayed.

   If you are using the Windows 2000 or Windows XP operating system, right-click the **Local Area Connection** icon and then click **Properties**.

4. Check that TCP/IP appears on the list of installed network components. If TCP/IP is not on the list, click **Add** to install this protocol using the Windows installation instructions, or refer to your network administrator.

Installing Nortel Reporting for Contact Center for a Business Communications Manager Installation

Follow the steps in this section to install Nortel Reporting for Contact Center for a Business Communications Manager installation.

1. Close any Windows programs that are open.

2. Start your Internet browser (such as Internet Explorer or Netscape) and connect to the Business Communications Manager. In the browser Address Bar, enter the IP Address of the Business Communications Manager in the following format: https://10.10.10.1/

   Remember to substitute the IP Address of *your* Business Communications Manager for the 10.10.10.1 shown in the example.

   Enter the username **nnadmin** and password in the BCM Login window. Consult your network administrator for the password, as this would have been changed from the default password of **PlsChgMe!** on first installation of Nortel Element Manager. The Welcome to BCM page appears.

3. Click **Business Applications**.
   The Business Applications page appears.

4. From the Contact Center Applications list, click **Reporting for Contact Center**. Information about the Nortel Reporting for Contact Center application appears. See Figure 10: Download the Reporting for Contact Center Software.


NORTEL
Home
Contact
Business Applications
Reporter Applications
Activity Reporter Basic
Activity Reporter
Contact Center Applications
Reporting for Contact Center
Multimedia Contact Center
ipView Softboard
Business Documentation
Business Documentation (PDF Format)
GetAdobe PDF Reader (opens new window)
Nortel Partner Program
Partner Program
This application is dependent on another application which requires a keycode.
Click here to connect to the Nortel Keycode Retrieval System
Reporting for Contact Center
packageforthewebTM
Download Reporting for Contact Center
See Important Notes Below
Nortel Reporting for Contact Center is a Windows®-based software application that provides Real Time screens and comprehensive historical management information on the day-to-day performance of your Business Communications Manager Contact Center system.
Nortel Reporting for Contact Center helps you manage the peaks and troughs in call traffic.
Monitored information includes:
Call waiting times
Queue lengths (that is, the number of calls waiting to be answered by your Skill set)
Agent status
Nortel Reporting for Contact Center provides a comprehensive range of management reports that have information critical for accurate business planning. Nortel Reporting for Contact Center has the ability to support multiple wallboards which can be individually configured to display the information that the agents require.
The Nortel Reporting for Contact Center is supported on the following operating systems:
Windows Vista Business, Ultimate
Windows XP Professional SP2

Figure 10: Download the Reporting for Contact Center Software

5. Click **Download Reporting for Contact Center** on the right side of the window. The **File Download** dialog box appears.

6. Select either **Run** to run this program from its current location, or **Save** to save this program to disk.

If you select **Save,** the Reporting for Contact Center executable file is downloaded to your PC. Go to the location where you downloaded the file and double-click the file to run it.

7. The Install Wizard shown in Figure 11: InstallShield Initialization dialog box appears. The wizard extracts the installation files required to install the Nortel Reporting for Contact Center files on the Web Host PC. Wait until the files are extracted.


Reporting for Contact Center - InstallShield Wizard
Extracting Files
The contents of this package are being extracted.
Please wait while the InstallShield Wizard extracts the files needed to install Reporting for Contact Center on your computer. This may take a few moments.
Reading contents of package...
InstallShield
< Back
Next >
Cancel

Figure 11: InstallShield Initialization dialog box

8. The installation will perform a compatibility check for minimum PC requirements to install Nortel Reporting for Contact Center, as shown in Figure 12: RCC Compatibility Check dialog box, with an exception of a Windows 2000 operating system where the minimum memory (or Random Access Memory) and processor speed are not verified.



Figure 12: RCC Compatibility Check dialog box

9. If the Web Host PC is compatible with Nortel Reporting for Contact Center, a RCC backup dialog box will be displayed, as shown in Figure 13: RCC Compatibility Check – creating backup files.



Figure 13: RCC Compatibility Check – creating backup files

Go to step 12.

If the Web Host PC is below the recommended minimum specification to install Nortel Reporting for Contact Center (for minimum specification requirements refer to Recommended Minimum PC Specification for BCM50 3.0 on page 15) an error message will be displayed.

An example error message for when there is insufficient memory on the Web Host PC to install Nortel Reporting for Contact Center is shown in Figure 14: RCC Compatibility Check – insufficient memory error message.


Reporting for Contact Center
System does not have enough RAM to run Reporting for Contact Center. Please upgrade your RAM and run the setup again.
Please consult RCC Setup and Operation Guide (RCC SUOG) for more details on system requirements for installing Reporting for Contact Center.
OK

Figure 14: RCC Compatibility Check – insufficient memory error message

Click **OK** on the error message displayed. The Nortel Reporting for Contact Center setup will stop and be rolled back.

10. To install Nortel Reporting for Contact Center increase the Web Host PC specification as requested in step 9.

11. Run the Nortel Reporting for Contact Center setup again as follows:
    - If the Reporting for Contact Center executable was saved to the Web Host PC, close any Windows programs and double-click on the executable file to run Nortel Reporting for Contact Center.
      Go to step 7.

    - If the Nortel Reporting for Contact Center download was run directly from the BCM50 3.0 Reporting for Contact Center download page, go back to step 1.

12. The **Choose Setup Language** dialog box will be displayed, as shown in Figure 15: Choose Setup Language dialog box, which allows you to select the default language for your installation of Nortel Reporting for Contact Center.

Figure 15: Choose Setup Language dialog box

Note: Each User of Nortel Reporting for Contact Center is assigned a language. You can have different languages in use by various Users at the same time.

This dialog box allows you to define the default language for the Login page and for the default Administrator. Click on the down arrow to the right of the dropdown box to display a list of languages.

When you have selected your language, click **OK**. To stop the installation, click **Cancel**.

13. If MDAC 2.8 is already installed on your PC, go to step 15.

    If you do not have Microsoft Data Access Components (MDAC) 2.8 already installed on your PC, you will be prompted to install it as a prerequisite for RCC, see Figure 16: InstallShield Requirements dialog box.


InstallShield Wizard
Reporting for Contact Center requires that the following requirements be installed on your computer prior to installing this application. Click OK to begin installing these requirements:
Status
Requirement
Pending
Microsoft Data Access Components (MDAC) 2.8
Pending
Microsoft SQL Server 2005 Express with Advanced Services
Pending
Microsoft Report Viewer
OK
Cancel

Figure 16: InstallShield Requirements dialog box

Click **OK** to install MDAC 2.8.

14. The MDAC 2.8 End User License Agreement dialog box appears. See Figure 17: MDAC 2.8 End User License Agreement dialog box.


Microsoft Data Access Components 2.8 Setup
End User License Agreement
Please read the following license agreement. Press the PAGE DOWN key to see the rest of the agreement. You must accept this agreement to install this software.
MICROSOFT CORPORATION END-USER LICENSE AGREEMENT
Microsoft Data Access Components 2.8
IMPORTANT-READ CAREFULLY: This End-User License Agreement ("EULA") is a legal agreement between you (either an individual or a single entity) and Microsoft Corporation for the Microsoft software product identified above, which includes computer software and may include associated media, printed
I accept all of the terms of the preceding license agreement
< Back
Next >
Cancel

Figure 17: MDAC 2.8 End User License Agreement dialog box

Select the **I accept all of the terms of the preceding license agreement** check box and click **Next**.

15. The setup will check for disk space, then display the MDAC installation dialog box, as shown in Figure 18: MDAC installation dialog box.



Figure 18: MDAC installation dialog box

Click **Finish** to begin the MDAC 2.8 installation.

16. After MDAC 2.8 is installed you will be asked to restart your PC for MDAC to operate correctly, see Figure 19: Microsoft Data Access Components system restart dialog box.


Microsoft Data Access Components 2.8 Setup
Restarting the System
The system will need to be restarted before Microsoft Data Access Components 2.8 will operate correctly.
Select whether to let setup restart the system for you, or to restart the system yourself.
Let setup restart the system now
I will restart the system myself
Click Finish to continue.
< Back
Finish
Cancel

Figure 19: Microsoft Data Access Components system restart dialog box

Click **Finish** to restart your PC.

Note: After the PC has rebooted, the Nortel Reporting for Contact Center installation will continue.

17. If you do not have Microsoft SQL Server 2005 Express with Advanced Services and Microsoft Report Viewer already installed on your PC you will be prompted to install them both as a prerequisite for RCC. See Figure 20: InstallShield RCC requirements for SQL Server and Report Viewer dialog box.


InstallShield Wizard
Reporting for Contact Center requires that the following requirements be installed on your computer prior to installing this application. Click OK to begin installing these requirements:
Status
Requirement
Pending
Microsoft SQL Server 2005 Express with Advanced Services
Pending
Microsoft Report Viewer
OK
Cancel

Figure 20: InstallShield RCC requirements for SQL Server and Report Viewer dialog box

Click **OK** to install both SQL Server 2005 Express with Advanced Services and Report Viewer automatically.

Note: This process can take several minutes and will also install Microsoft .Net Framework 2.0 if required. See Figure 21: InstallShield RCC requirements dialog box.


InstallShield Wizard
Reporting for Contact Center requires that the following requirements be installed on your computer prior to installing this application. Click OK to begin installing these requirements:
Status
Requirement
Installing
Microsoft SQL Server 2005 Express with Advanced Services
Pending
Microsoft Report Viewer
Configuring Microsoft(R) .NET Framework
OK
Cancel

Figure 21: InstallShield RCC requirements dialog box

18. After the RCC prerequisite software have been installed the InstallShield RCC Welcome dialog box appears, as shown in Figure 22: InstallShield Wizard RCC Welcome dialog box.


InstallShield Wizard
Welcome to the InstallShield Wizard for Reporting for Contact Center
The InstallShield® Wizard will install Reporting for Contact Center on your computer. To continue, click Next.
< Back
Next >
Cancel

Figure 22: InstallShield Wizard RCC Welcome dialog box

To begin the RCC installation click **Next**.

To cancel the installation procedure, click **Cancel**.

19. The License Agreement for Nortel Reporting for Contact Center dialog box appears, as shown in Figure 23: License Agreement dialog box.


Reporting for Contact Center
License Agreement
Please read the following license agreement carefully.
Press the PAGE DOWN key to see the rest of the agreement.
Nortel Corporation
Nortel Reporting for Contact Center
SOFTWARE LICENCE AGREEMENT
CAUTION! PLEASE READ THIS BEFORE INSTALLING OR USING THIS SOFTWARE.
1. Grant of Licence
Grant of Licence from Nortel Corporation ("Nortel"). This document ("Agreement"), is the
Do you accept all the terms of the preceding License Agreement? If you select No, the setup will close. To install Reporting for Contact Center, you must accept this agreement.
Print
InstallShield
< Back
Yes
No

Figure 23: License Agreement dialog box

20. Read the Software License Agreement before proceeding. To proceed with the installation, click **Yes**.

    To return to the Welcome dialog box, click **Back**.

    To cancel the installation, click **No**. A warning message will be displayed asking the user for confirmation to quit the RCC installation, as shown in Figure 24: Exit Setup warning message box.


Exit Setup
Setup is not complete. If you quit the setup program now, the features you requested to add/remove will not be installed/uninstalled.
You may run the setup program at a later time to complete the operations.
Are you sure you want to quit the setup?
Yes
No

Figure 24: Exit Setup warning message box

Click **Yes** to quit the installation. The InstallShield Wizard Completed dialog box appears. Click **Finish** to exit the Wizard.

21. The Choose Destination Location dialog box shown in Figure 25 : Choose Destination Location dialog box appears.


Reporting for Contact Center
Choose Destination Location
Select folder where setup will install files.
Setup will install Reporting for Contact Center in the following folder.
To install to this folder, click Next. To install to a different folder, click Browse and select another folder.
Destination Folder
C:\...\Nortel\Reporting for Contact Center\
Browse...
InstallShield
< Back
Next >
Cancel

Figure 25 : Choose Destination Location dialog box

22. Nortel recommends that you accept the location specified in the dialog box. If you do not wish to install Nortel Reporting for Contact Center on the default drive (C:\), click **Browse** to choose a new destination.

    To proceed with the installation, click **Next**.

    To cancel the installation, click **Cancel**.

23. The Setup Status dialog box shown in Figure 26: Setup Status dialog box appears.



Figure 26: Setup Status dialog box

The Setup Status dialog box shows the progress of the installation. To cancel the installation at this stage, click **Cancel.**

24. The message shown in Figure 27: Java installation dialog box appears. Wait for the installation to complete.

Figure 27: Java installation dialog box

Note: The Java Runtime is not installed into the same folders as Nortel Reporting for Contact Center; it is installed into \Java on the target hard drive.

25. When installation is complete, the InstallShield Wizard Complete dialog box shown in Figure 28: Installation Complete dialog box appears.


Reporting for Contact Center
InstallShield Wizard Complete
The InstallShield Wizard has successfully installed Reporting for Contact Center. Before you can use the program, you must restart your computer.
Yes, I want to restart my computer now.
No, I will restart my computer later.
Installation is not yet complete. After the reboot a user with local administration rights must log in to continue with the installation.
< Back
Finish
Cancel

Figure 28: Installation Complete dialog box

Note: Before Nortel Reporting for Contact Center can operate correctly, you must restart your Web Host PC.

For the installation to restart the PC, select **Yes, I want to restart my computer now**, and then click **Finish**.

To complete the installation without restarting your PC at this time, select **No, I will restart my computer later**, and then click **Finish**.

26. After you have rebooted your PC and logged back on the Reporting for Contact Center RCC Monitor splash screen will automatically appear, as shown in Figure 29: RCC Monitor splash screen.

Figure 29: RCC Monitor splash screen

27. The RCC Database Installer Utility (DBI) will then be launched. See Figure 30: RCC Database Installer Utility. The DBI launches and configures the database. It performs several steps and displays its status during each step.



Figure 30: RCC Database Installer Utility

Note: This utility can take several minutes to execute. During the **Create Tables** step, there will be a long pause of approximately five minutes while the **strings.sql** table is created. This is normal and is due to its large size.

28. When the RCC DBI has completed it will launch the Install Verification Utility (IVU), refer to Install Verification Utility on page 46, and also the Print Caller Service (PCS), refer to Print Caller Service on page 48.

Install Verification Utility

The Install Verification Utility, also known as IVU, checks all the components of RCC to ensure they have been installed and configured correctly. See Figure 31: RCC Install Verification Utility.



Figure 31: RCC Install Verification Utility

The IVU checks the following:

- SQL Server installation
- Database Status
- Java Runtime Environment

- Microsoft .Net Framework
- RCC Ports and Firewalls
- Internet Information Services (IIS)
- Report Service
- BCM connection

The last check in the IVU is to verify a BCM connection from the Web Host PC. The IVU will request BCM connection data. A BCM Connection Data dialog box will open, as shown in Figure 32: BCM Connection Data dialog box.



Figure 32: BCM Connection Data dialog box

The BCM connection details requested by IVU are as follows:

1. **IP Address/Network Name** – enter the IP Address or the Network name of the BCM, also known as Contact Center, platform.

2. **Port** – this should be defaulted to the correct port number of **8088**.

3. **CCRS Password** – when Nortel Reporting for Contact Center requests Real Time or Historical Report data from the Contact Center, a password is included in the data request. This password is set within the Contact Center using CallPilot Manager.

   The default CCRS password is **CCRS**.

Click **OK** to submit the BCM Connection data.

To verify the BCM IP Address and CCRS password entered, the IVU will connect to the BCM to get some Real Time and Historical Report data, as shown in Figure 33: RCC Install Verification Utility verifying BCM connection.



Figure 33: RCC Install Verification Utility verifying BCM connection

After successful connection to the BCM, a message box will be displayed to confirm whether you want to save the BCM connection settings. See Figure 34: Save BCM connection settings message box.


Save BCM connection settings?
Both realtime and historical requests were successful.
IP Address/Network Name: 30.30.30.6
Port: 8088
Do you want to save your chosen BCM connection settings into the database?
Yes
No

Figure 34: Save BCM connection settings message box

Click **Yes** to save the settings to the RCC database.

The IVU window will display a successful verification message and links at the bottom of the window, as shown in Figure 35: RCC Install Verification Utility verification success.



Figure 35: RCC Install Verification Utility verification success

Click **Click Here to launch RCC** to launch Nortel Reporting for Contact Center.

To re-run the IVU click **Refresh**. Otherwise, to close IVU, click the Close button on the top right hand corner of the IVU window.

Print Caller Service

The Print Caller Service, also known as PCS, can run as a desktop application or a Windows service. By default the PCS will run as a desktop application and a user must be logged on to the PC for it to operate normally. The user can change the settings of the PCS to allow it to run as a Windows service and consequently are not required to log on to the PC for their *ad hoc* reports and Print Schedules to be served.

> **Note:** For Microsoft Windows Vista users PCS must be set as a Windows service, refer to PCS as a Windows service on page 52, to allow Print Caller Service logs to be created.
>
> For more information on RCC logs refer to Logging on page 78.

PCS as a desktop application

When PCS is running as a desktop application it will run in the background and display a system tray icon. An information bubble will be displayed, as shown in Figure 36: Print Caller Service information balloon, indicating that PCS has successfully started up and is serving print requests.



Figure 36: Print Caller Service information balloon

Stopping the PCS desktop application

To stop the Print Caller Service, right-click the RCC Print Caller Service icon from the system tray and choose **Stop Print Caller Services**, see Figure 37: Print Caller Service menu.



Figure 37: Print Caller Service menu

Alternatively, stop the PCS through the RCC Print Caller Service window by the following:

1. Double-click the RCC Print Caller Service system tray icon, or right-click over the icon and choose **Open**, see Figure 37: Print Caller Service menu. You can also click the Print Caller Service information balloon, as shown in Figure 36: Print Caller Service information balloon.

   The RCC Print Caller Service window will open, as shown in Figure 38: RCC Print Caller Service window.



Figure 38: RCC Print Caller Service window

2. Click **Stop** to stop the PCS running.

3. The Status in the RCC Print Caller Service window will change and the **Start** button will be displayed in order for the user to restart the PCS, as shown in Figure 39: RCC Print Caller Service window – PCS stopped.



Figure 39: RCC Print Caller Service window – PCS stopped

The RCC Print Caller Service system tray icon will have a red line across it and a warning balloon informing the user that the PCS has stopped running and that print schedules can no longer print reports. See Figure 40: Print Caller Service warning balloon.


RCC Print Caller Service
RCC Print Caller service is stopped and can no longer print reports. Click here to start RCC print caller services.
10:07

Figure 40: Print Caller Service warning balloon

Restarting the PCS desktop application

Perform either option to restart the PCS:

Option 1

- Right-click the RCC Print Caller Service system tray icon and choose **Start Print Caller Services**, as shown in Figure 41: Print Caller Service menu – Start function.



Figure 41: Print Caller Service menu – Start function

Or,

Option 2

- Follow the steps in the section Stopping the PCS desktop application, on page 50, where step 2 will display the **Start** button to restart the PCS.

PCS as a Windows service

Perform the following steps to set the PCS operational mode to run as a Windows service:

1. Right-click the RCC Print Caller Service system tray icon and choose **Run as Windows Service** from the menu, see Figure 37: Print Caller Service menu.

   Alternatively, open the RCC Print Caller Service window and select the **Run as Windows Service** check box and click **Apply**, as shown in Figure 42: RCC Print Caller Service window - Windows service mode.

Figure 42: RCC Print Caller Service window - Windows service mode

   To cancel the PCS Windows service mode selection click **Close**.

2. A confirmation message box will be displayed informing the user that the PCS operation mode will be changed from a background application to a Windows service. See Figure 43: RCC Print Caller Service mode change message box.

RCC Print Caller Service
You are about to change RCC Print Caller to run from background application mode to Windows service mode.
You will be asked to provide username and password to gain access to the network printers. This information will be used in the future startup of the Print Caller Service. To reflect these changes RCC Print Caller will need to restart your system at later stage.
Are you sure to change the run mode of RCC Print Caller Service?
Yes
No

Figure 43: RCC Print Caller Service mode change message box

   Click **Yes** to proceed with the mode change.

3. The Set Service Login dialog box will appear, as shown in Figure 44: Set Service Login dialog box. Enter the username and password used to access networked printers configured on the Web Host PC.


Set Service Login
Username:
.\Developer
Password:
Confirm password:
Please enter your Windows username and password. These are required in order to startup the Print Caller Service and to it allow to access network printers and print schedules. This username will be used for future startups of the Print Caller Service.
OK
Cancel

Figure 44: Set Service Login dialog box

4. Click **OK** to install RCC Print Caller Services Windows service and to save the log on settings.

5. The user will be prompted to reboot their PC to enable the RCC Print Caller Services Windows service settings, as shown in Figure 45: RCC Print Caller Services settings changed message box.


RCC Print Caller Settings changed
These changes will take effect after you restart the PC.
Please save any unsaved data and close all running programs. Click Restart Now when ready.
Restart now
Restart later

Figure 45: RCC Print Caller Services settings changed message box

Click **OK**.

After the PC has restarted, the user is not required to log on to the PC again for RCC Print Caller Services to run as a Windows service and for *ad hoc* reports and Print Schedules to be served.

To uninstall the PCS as a Windows service and run it again as a desktop application, perform the following steps:

1. Right-click the RCC Print Caller Service system tray icon and choose **Run as background application**. See Figure 46: Print Caller Service menu for Windows service.



Figure 46: Print Caller Service menu for Windows service

2. A confirmation message box will be displayed to verify the run mode change of the PCS from a Windows service to a background application, as shown in Figure 47: RCC Print Caller Service mode change to background application message box.


RCC Print Caller Service
You are about to change RCC Print Caller to run from Windows service mode to background application mode
Are you sure to change the run mode of RCC Print Caller Service?
Yes
No

Figure 47: RCC Print Caller Service mode change to background application message box

Click **Yes**.

The user does not have to restart their PC for PCS to run as a background application. Ensure that the Web Host PC is logged on for *ad hoc* and scheduled reports to print.

Stopping the PCS Windows service

To stop the Print Caller Service Windows service, perform either option, as follows:

Option 1

- Using the RCC Print Caller Service window, as follows:
  1. Right-click the RCC Print Caller Service system tray and choose **Open**. See Figure 46: Print Caller Service menu for Windows service.

     Alternatively, double-click the RCC Print Caller Service system tray icon, or click the Print Caller Service information balloon, see Figure 36: Print Caller Service information balloon.

  2. The RCC Print Caller Service window will open, as shown in Figure 48: RCC Print Caller Service window – Windows service mode.



Figure 48: RCC Print Caller Service window – Windows service mode

Note: The **Run as Windows Service** check box will be selected to indicate that the PCS is running as a Windows service.

3. Click **Stop** to stop the PCS running.

4. The Status in the RCC Print Caller Service window will change and the **Start** button will be displayed in order for the user to restart the PCS, as shown in Figure 49: RCC Print Caller Service window – PCS stopped as a Windows service.



Figure 49: RCC Print Caller Service window – PCS stopped as a Windows service

The RCC Print Caller Service system tray icon will have a red line across it and a warning balloon informing the user that the PCS has stopped running and that print schedules can no longer print reports. See Figure 40: Print Caller Service warning balloon.

Or,

Option 2

- Stop the PCS Windows service through the Services window, as follows:

1. From the Start menu, click on **Settings > Control Panel > Administrative Tools > Services.**

2. Right-click **RCC Print Caller Services** and choose **Stop** or, in the Extended window, select **RCC Print Caller Services** and click **Stop**.

3. Close the Services, Administrative Tools and Control Panel windows.

Restarting the PCS Windows service

To restart the PCS Windows service, perform either option, as follows:

Option 1

- Follow the steps in the section Stopping the PCS Windows service, on page 54, where step 3 will display the **Start** button to restart the PCS;

Or,

Option 2

- Restart the PCS Windows service through the Services window, as follows:

1. From the Start menu, click on **Settings > Control Panel > Administrative Tools > Services.**

2. Right-click **RCC Print Caller Services** and choose **Start**, or in the Extended window, select **RCC Print Caller Services** and click **Start**.

3. Close the Services, Administrative Tools and Control Panel windows.

To quit the PCS

Perform the following steps to quit the PCS:

1. Right-click the RCC Print Caller Service system tray icon and choose **Exit**.

2. A message prompt will be displayed to confirm quitting the PCS program, as shown in Figure 50: Print Caller Service shut down warning message.


RCC Print Caller Service
RCC Print Caller Service is running to serve all of your print requests. By terminating it, you won't be able to print scheduled reports. Are you sure you want to terminate it?
Yes
No

Figure 50: Print Caller Service shut down warning message

Click **Yes**.

The PCS program will shut down and *ad hoc* reports and Print Schedules will no longer print reports.

Administration 4

Logging In

Follow the steps in this section to log on to Nortel Reporting for Contact Center as an Administrator:

1. Using Internet Explorer, go to your Nortel Reporting for Contact Center Web pages Login page.

   The URL is http://[*Name of Web Host PC*]/RCC

   Where *NameOfWebHostPC* is the network name or IP Address of the Web Host PC.

   The Login page appears. See Figure 51: Login page.

   Note: If you are using the browser on the Web Host PC, you can replace *NameOfWebHostPC* with **localhost**.

   Note: You can add the Login page to your Internet Favorites. To add this page to your favorites in Internet Explorer, press **Ctrl**+**D** when you are at the Login page, or from the menu bar select **Favorites > Add to favorites.**



Figure 51: Login page

2. Enter the username **admin** and the default password **0000,** and click **Login**.

   Note: After an upgrade from Nortel Reporting for Contact Center version 2.4 to 2.5, the password is defaulted back to **0000**.

   You must change the default password the first time you log on, including after an upgrade from Nortel Reporting for Contact Center version 2.4 to 2.5. See Changing Default Password.

Changing Default Password

Perform the following steps to change the default password:

1. When you first log on, the Change Password dialog box appears. See Figure 52: Change Password page.

   Your password can be from 1 to 10 characters, including upper and lowercase letters, and digits. The password can be anything other than **0000**.

   Enter your new password in the **New password** field.



Figure 52: Change Password page

Your password can be from 1 to 10 characters, including upper and lowercase letters, and digits. The password can be anything other than **0000**.

Enter your new password in the **New password** field.

2. Re-enter your password in the **Confirm password** field.

   If the passwords you entered are not the same, you are informed that the password and confirmation do not match, and you must re-enter the password in both fields.

3. Click **Submit**.

   If you successfully entered the new password, the Contact Center Connection page as shown in Figure 53: Contact Center Connection page appears.

   Note: The Administrator will be re-directed to the Contact Center Connection page on first log on after a fresh installation of Nortel Reporting for Contact Center, or after an upgrade from Nortel Reporting for Contact Center version 2.4 to 2.5.

Contact Center Connection

The Contact Center Connection page allows you to specify the network identifier (IP address or Network name) of the Contact Center platform.

Typically, the Contact Center Connection page appears only once, after you first log on as an Administrator . If the Contact Center Connection information is incomplete or incorrect, the Contact Center Connection page appears each time you log on as an Administrator.

For example, if you add a new Network Card to the Web Host PC, you must select an IP address for the Web Host PC to communicate with the wallboards. In this case, the Contact Center Connection page appears so that you can select the IP address.

If you do not select the Contact Center Connection option from the menu, the page automatically appears after you log on, as shown in Figure 53: Contact Center Connection page.



Figure 53: Contact Center Connection page

Perform the following steps to configure the Contact Center Connection page:

1. In the **IP Address/Network name** field, enter the IP Address or the Network name of the Contact Center platform. If you do not know what information to enter, consult the Local Area Network Administrator for your site.

   Note: Check that Reporting for Contact Center is configured to point at the IP Address of the Contact Center. For BCM50 3.0 system this will be the network IP address of the BCM.

2. The **Port** field will be defaulted automatically to the correct port number of 8088 for connection to a BCM50 3.0 system.

3. When Nortel Reporting for Contact Center communicates with the Contact Center to request Real Time or Historical Report data, it includes a password in the data request. This allows the Contact Center to verify that the application requesting the data is authorized to receive it.

   This password is set within the Contact Center using CallPilot Manager. In the **CCRS password** field, enter the set password.

   Note: The default CCRS password is CCRS. If the default password is not accepted the password might have been changed in the Contact Center from within CallPilot Manager.

4. In the **Confirm CCRS password** field, re-enter the set password.

5. In the **Make data requests every** list specify how frequently the Web Host PC communicates with the Contact Center in order to obtain reporting data. The typical setting is 15 minutes.

6. In the **Select an IP Address** list, select the IP address (Network Interface Card) with which you wish to communicate with the wallboards. If the Web Host PC has more than one IP Address (because it has more than one Network Interface Card configured) the list is populated with the IP addresses configured for the Web Host PC. Select which Network Interface Card to use for communication with the wallboards. The Network Interface Cards are identified in the list by their configured IP Addresses.

   Select the IP Address that is configured on the Network Interface Card connected to the same network as the wallboards. Note that this IP Address is not the IP Address of the wallboard. This address is the IP Address configured for the Network Interface Card in the Web Host PC.

   Note: If you add a new Network Interface Card or other network device, such as a USB Bluetooth device, or if you enable a disabled Network Interface Card, then you must reboot your Web Host PC so that the new device is detected and presented in the **Select An IP Address** list.

7. From the **Wallboard and Refresh Real Time Interval** list, select your refresh interval for the Wallboard and Real Time displays. The two available options are 1 second (default) and 3 seconds.

   Note: This setting applies only to the refresh rate of the display. Wallboard and Real Time information is always calculated to the second. If, for example, you select 3 seconds as your refresh interval, your display updates every 3 seconds but your data is calculated to the second.

Wallboard and Real Time Refresh Interval : 1 Second(s)
Download Contact Center Data :
All Data
Only Data starting from : 2004/03/01

Figure 54: Download Contact Center Data options

8. On first installation of Reporting for Contact Center the **Download Contact Center Data** options are given, see Figure 54: Download Contact Center Data options. The User can select whether to download all data from the Contact Center by selecting **All Data**, or the User can select **Only Data starting from** and click on the calendar icon to the right to select a start date from when data should be downloaded from the Contact Center.
9. Click **Submit**.

   The Download Status window appears. This displays the progress of the Contact Center download. See Figure 55: Download Status window.


Nortel Reporting for Contact Center - Windows Internet Explorer
25%
Status:
Time: 00:00:11
Processing Calls From: 04 Apr 2007 09:00:00
Total Contact Center Calls in the Database: 5

Figure 55: Download Status window

Five parameters are provided in the Download Status window, as follows:

i. **Data download progress** – this indicates the percentage of data download completion by way of a progress bar and a percentage. When 100% download completion is reached, the progress bar will display the text:

RCC Database Update Complete

Note: After Reporting for Contact Center is installed, it queries the Contact Center for any Contact Center data that the Contact Center has accumulated.

ii. **Status** – an indicator light will be displayed. A green indicator light shows the successful downloading of data from the Contact Center. The **Status** indicator will turn red if Reporting for Contact Center encounters problems downloading Contact Center data. An error message will be displayed directly below the Status field, indicating the problem. Refer to the *Reporting for Contact Center Troubleshooting and Maintenance Guide* (NN40020-403) on the type of error messages that can be displayed and how to troubleshoot them.

iii. **Time** – this is the time in hours, minutes, and seconds that the current download has been running. This data is updated every 9-10 seconds.

iv. **Processing Calls From** – this displays the start date and time of the current data being processed. Reporting for Contact Center will request data from the Contact Center from this date to the latest call data in the Contact center. This is the download period. **Data download progress** indicates how far through the download period the download process is in terms of time, not in terms of calls.

v. **Total Contact Center Calls in the Database** – this indicates the total amount of calls stored in the Web Host PC database.

Note: The time to download the historical data from the Contact Center and to store it in the Web Host PC database depends on the amount of time the Contact Center has been recording historical data prior to being connected to the Web Host PC and the amount of call traffic that your Contact Center handles.

As a general guide, 30,000 calls take between 6 and 18 hours to download, depending on the level of network traffic and the speed of your Web Host PC.

Note: You can use your PC as normal during the download, but do not reset it or power it off.

When the download is complete, the Data download progress field shows a 100% complete status.

Your browser page may time out before the download is complete. This is not an error. Microsoft Internet Information Services has a setting that dictates how long it waits before closing a web page. As the download completes, you are informed of the status in the Download Status field. The Administration Menu appears, refer to Administration Menu on page 64.

Administration Menu

When an Administrator logs in (unless they are logging in with the default password of 0000), they view the Administration Menu page. See Figure 56: Administration Menu page.

> **Note:** To remind you that you logged in as an Administrator, Administration appears in the blue bar at the top of each Administration page.



Figure 56: Administration Menu page

The available Administrator options appear in the navigation pane on the left side of the page. For information about the Contact Center Connection, refer to Contact Center Connection on page 60. The following sections describe the System Administration, Maintenance, Company Details, and Reporting options.

System Administration

Select **System Administration** to view the **System Administration Menu** page shown in Figure 57: System Administration Menu page.



Figure 57: System Administration Menu page

The System Administration Menu provides the following options:

- System Admin Settings — change the username and the password for the default Nortel Reporting for Contact Center Administrator.
- User Admin — create Users.
- Skillset Assignment — assign Skillsets to Users.
- System Configuration report — view and print the System Configuration report.

System Admin Settings

System Admin Settings is a special utility that allows you to change the settings for the single, pre-defined Administrator that is supplied, ready-defined, with Nortel Reporting for Contact Center. You can use System Admin Settings to change the name of the System Administrator or change their password, or both. In either case, you must enter the current System Administrator password to confirm that you have authority to make these changes.

> **Note:** Do not use System Admin Settings to change the username and password of other Users who are configured as Administrators. To change the details of those Administrators, use the User Admin Edit feature, described in User Admin.

Select **System Admin Settings** to view the **System Administrator details** page, shown in Figure 58: System Administrator details page.



Figure 58: System Administrator details page

To change the name of the System Administrator, provide a new name in the **Please enter new username** field, and the current Administrator password in the **Please enter old password** field.

To change the password, provide the new password in the **Please enter new password** field, and confirm the password by entering the same password in the **Please confirm new** password field.

After you make the necessary changes, click **Submit**. The **System Administration Menu** page shown in Figure 57: System Administration Menu page appears.

User Admin

The User Admin option allows you to add, delete, edit the settings for, or reset the password for a User.

> **Note**: A User is not an Agent. A User is someone you wish to have access to the Nortel Reporting for Contact Center system, to monitor Skillsets through the Real Time screens and to be able to obtain Historical Reports on those Skillsets.

You do not need to enter all your Contact Center Agents into Nortel Reporting for Contact Center (although you can, if you wish). Typically, you enter Skillset Supervisors and other Management personnel who need information about the performance of the Contact Center.

Select **User Admin** to view the **User Admin** page, shown in Figure 59: User Admin page.



Figure 59: User Admin page

Add Users

The first time you see this page, no Users are defined. To add users, click **Add**. The Add User page, as shown in Figure 60: Add User page appears.



Figure 60: Add User page

This page allows you to enter the details of the new User. Follow these steps:

1. In the **First name** and **Last name** fields, enter the User's first and last names.

2. In the **RCC Username** field, enter the RCC Username, which is the name the User will use to log on to Nortel Reporting for Contact Center.

3. From the **Language** list, specify the User language preference, which dictates the language used to display the Nortel Reporting for Contact Center Web page.

4. If the User is able to configure wallboards (for their assigned Skillsets), select the **Assign Wallboards** check box. See Table 1: Administrator and User Permissions.

5. If the User is also an Administrator, select the **Administrator** check box whether the User is a regular User or an Administrator.

Note: The System Administrator, Users created as Administrators, Users who can Assign Wallboard and Standard Users have different administration capabilities regarding other Users, Skillset Assignment, and Wallboard Assignment. See Table 1: Administrator and User Permissions.

Table 1: Administrator and User Permissions

Permission Level	Capabilities
Regular Users (Standard Users)	These are Users who were created without either the Administrator or the Assign Wallboards check boxes selected. These Users cannot perform configuration of other Users, and they cannot change their own settings. They also cannot assign or work with Wallboards. Regular Users have access only to the Skillsets that were assigned to them by the System Administrator.
Users with the Assign Wallboard Box Checked (Wallboard Users)	These are Users who were created without the Administrator check box selected. These Users cannot perform configuration of other Users, and they cannot change their own settings. They can assign and work with Wallboards. Wallboard Users have access only to the Skillsets that were assigned to them by the System Administrator.
Users with the Administration Box Checked (User Administrators)	These are Users who were created with the Administrator check box selected. These Users can perform configuration and editing activities on other Users, including creating Users and assigning Skillsets to them. They cannot change their own settings, however, apart from resetting their own password. If the Wallboard check box was selected when their own account was created, they can assign and work with Wallboards. User Administrators have access only to the Skillsets that were assigned to them by the System Administrator. You should designate a User as an Administrator only if the designation is required so that the User can specify and change fundamental configuration settings within Nortel Reporting for Contact Center.
System Administrator	This is the default Administrator account that is created when Nortel Reporting for Contact Center is installed. This User has full access to the system and to all configuration options. They can create, edit, and delete Users, and they can assign Skillsets to Users. They can also reset User passwords, including the System Administrator's password. Note that they are the only user who can do this. The System Administrator has access to any Skillset.

Note: The default password for all new Users is 0000. The first time they login to Nortel Reporting for Contact Center they are prompted to change their password.

In the example shown in Figure 61: Details for new User Mary Smith, the new user Mary Smith has been added, with the RCC Username of **MaryS**, she is going to receive the Web pages in English, and, while she can configure wallboards for her assigned Skillsets, she is not a full Administrator.



Figure 61: Details for new User Mary Smith

6. Click **Submit** to save the details of the newly entered User.

7. A dialog box asks whether you wish to add more Users. If you choose to add more users, click on the **OK** button, otherwise click on **Cancel**. If you had clicked on **OK**, the Add User fields are cleared and you can enter the details of your next new User. If you decide not to add more Users at this time, you are returned to the User Admin page shown in Figure 59: User Admin page.

The newly added User now appears in the list of configured users on the User Admin page. To view details about a specific User, select the User's name from the list. Click the **Edit** button next to selected User to Edit the details of the user (see Edit Users). To Delete the User from the system click on the **Delete** button (see Delete Users). To reset their password to 0000 if they have forgotten their password click on the **Reset Password** button (see Reset Password).

Edit Users

To edit User details, select the User from the list of configured users and click **Edit.** The Edit user page, shown in Figure 62: Edit User page appears.



Figure 62: Edit User page

To edit User details, make any necessary changes, and then click **Submit**. For more information about the fields on the Edit User page, refer to Add Users.

Delete Users

To delete a User, select the User from the list of configured users and click **Delete**.

Note: After you delete a User, you cannot retrieve the deleted User for later use. For any subsequent inclusion of that User, later you must use the Add User page (see Figure 60: Add User page) and re-enter User details.

When you click **Delete** you are prompted to confirm that you wish to remove the User. If you do not wish to remove the User, click **Cancel**; if you are certain you wish to remove the User, click **OK**.

In either case, the User Admin page appears. See Figure 59: User Admin page. If you removed a User, that User name no longer appears in the list of configured Users.

Reset Password

Use the **Reset Password** option when a User has changed their password and forgotten what the password is.

This option allows you to reset the User password to 0000.

When the User next logs on, they use the password 0000, and they must then select a new password.

Select the User name from the list of configured users and click **Reset Password.** You are prompted to confirm that you wish to reset the password for the User. If you do not wish to reset the password, click **Cancel.** To reset the password, click **OK**.

In either case, the User Admin page appears. See Figure 59: User Admin page.

Skillset Assignment

The Skillset Assignment option allows you to assign Skillsets to Users. Assigning Skillsets to a User allows the User to view those Skillsets in the Real Time screens and to obtain Historical Reports on those Skillsets.

You can assign multiple Skillsets to a User, and a Skillset can be assigned to multiple Users.

Select **Skillset Assignment** from System Administration Menu shown in Figure 57: System Administration Menu page. The Skillset Assignment page shown in Figure 63: Skillset Assignment page appears.



Figure 63: Skillset Assignment page

The Skillset Assignment page lists each configured User. In Figure 63: Skillset Assignment page, Mary Smith is the only configured User. Follow the steps in this section to assign Skillsets.

1. Click **Assign** to view the Assigned Skillsets page, shown in Figure 64: Assigned Skillsets page.



Figure 64: Assigned Skillsets page

Note: The Skillset names shown in Figure 64: Assigned Skillsets page are intended as examples only. Your copy of Nortel Reporting for Contact Center displays the Skillset names you have set up in the Contact Center using CallPilot Manager.

Note: The Skillset names are obtained automatically from the Contact Center. Your copy of Nortel Reporting for Contact Center must be connected to the Contact Center for a few moments in order for the Skillset names to appear.

2. To assign a single Skillset, select the Skillset in the **Unassigned Skillsets** list, then click the right arrow button (>). The assigned Skillset appears in the Assigned Skillsets list.

3. Continue assigning Skillsets until you assign all the Skillsets you wish to assign to this User. In the example shown in Figure 65: Skillsets Assigned to User Mary Smith, the User Mary Smith is assigned two Skillsets: SKILL1 and SKILL3.



Figure 65: Skillsets Assigned to User Mary Smith

4. To move a Skillset to the Unassigned Skillsets list, select the Skillset name in the **Assigned Skillsets** list and click the left arrow button (<)

   Note: Click the double right arrow button (>>) or the double left arrow button (>>) to assign or un-assign all the Skillsets.

   Note: To assign or un-assign more than one Skillset name in the Assigned Skillsets or Unassigned Skillsets list, hold down the Control (**Ctrl**) key and click different Skillset names in the list. Click the > or < button to assign or un-assign those selected Skillsets in one step.

5. When you have assigned (or unassigned) the Skillsets for a User, click **Submit**. The Skillset Assignment page shown in Figure 63: Skillset Assignment page appears.

Maintenance

The Maintenance option allows you to check the System Status and to start or stop the XML data feed logging.

Select **Maintenance** to view the Maintenance Menu page, shown in Figure 66: Maintenance Menu page.



Figure 66: Maintenance Menu page

The Maintenance Menu provides the following options:

- System Status
- Logging

System Status

Select **System Status** to view the System Status page shown in Figure 67: System Status page. This page provides a variety of information relating to the current status of Nortel Reporting for Contact Center.



Figure 67: System Status page

From this page you can see the Web Host PC's Web Server details, RCC Database connection status and BCM System Information including version numbers and the Contact Center Status which refers to the connection status between Reporting for Contact Center and the BCM. You can also open the Download Status window from the link **Click Here to open the Download Status window**. The Current RCC Network Port Status information determines whether the current PC viewing this page can establish a connection to the ports listed. If any of the ports are blocked to the Web Host PC it will identify which ones and the next steps to take to resolve this.

The Java coffee cup and status message indicate that the Java Runtime Environment is installed on this PC and what version is currently active.

Under normal operation you need only to refer to this page upon instruction of Support Personnel.

Logging

Select **Logging** to view the Logging Menu page shown in Figure 68: Logging Menu page.



Figure 68: Logging Menu page

Various diagnostic logs are always running when Nortel Reporting for Contact Center is operational. The Logging Menu allows you to Archive the current log files and download any previously archived log files.

To Archive the current log files click the **Archive Logs** button. This will create a single .zip archive file of the current log files. A new entry will appear in the list of archived files table, following the **Log files location** on the Logging Menu page. Recently created log file archives are indicated by a yellow star.

To stamp the Real Time log click the **Stamp Real Time Log** button. This will stamp the Real Time log constantly for 15 seconds. As the Real Time log can be quite large this option is useful for tracking down a problem to a specific time.

Clicking the **Stamp Real Time Log** button will disable the button for 15 seconds. Stamping cannot be initiated again in this time until 15 seconds have passed. After this time has elapsed the button will be enabled.

To download a log file archive click the **Download Logs** button next to the desired archive and save it to a location on your computer.

Note: The maximum number of archives you can create is 5. When a 6th archive is created it will automatically delete the oldest archive. The file naming convention includes (in the same order) the year, month, day, hour, minute and second that the archive was created, this can be used to determine how old the log file archive is. To view the contents of the archive you will need to have either WinZip, WinRAR or any other compatible zip file viewer installed. The default compressed folder viewer that comes with Windows XP and above will not work with these archives.

Company Details

The Company Details page allows you to enter details about your company or site. See Figure 69: Company Details page. To view the page, select **Company Details**.



Figure 69: Company Details page

Completing this page is not a requirement for the correct operation of Nortel Reporting for Contact Center. The page provides a means of recording where the software is installed.

After the company details are entered, click **Submit** to save the details. The company details will be available in the System Configuration report and the company name will be displayed on all report headers.

From the Company Details page, the user will be returned back to the Administration Menu page.

Reporting

Click **Reporting** to view the Main Menu page, shown in Figure 70: Main Menu page.

This is the page all regular Users (that is, non-Administrative Users) view when they log on.

This option allows an Administrator to use the Nortel Reporting for Contact Center as though they were a User, to view Real Time screens, and to access the Historical Reports.

For more information, refer to Using Reporting for Contact Center.



Figure 70: Main Menu page

Using Reporting for Contact Center 5

Logging On

Follow the steps in this section to log on to Nortel Reporting for Contact Center for all Users.

1. Use Internet Explorer to go to the URL of your Nortel Reporting for Contact Center Web pages Login page.

   The URL is http://*NameOfWebHostPC*/RCC

   Where *NameOfWebHostPC* is the network name or, IP Address of the Web Host PC.

   The Login page appears. See Figure 51: Login page.

   Note: If you are using the browser on the Web Host PC, you can replace NameOfWebHostPC with localhost.

   Note: You can add the Login page URL to your Internet Favorites. To add this page to your favorites in Internet Explorer, press **Ctrl**+**D** when you are at the Login page, or click **Favorites, Add to favorites.**

2. You must provide a valid username and a password to gain access to the features of Nortel Reporting for Contact Center. Before you attempt to log on, ensure that an Administrator has created a username for you.

   The first time you log on, your password is set to the default of 0000.

3. In the **Username** field, enter the Username you have been assigned. In the **Password** field, enter the default password of 0000.You must change your password after you first log on. The Change Password page shown in Figure 71: Change Password page appears.



Figure 71: Change Password page

In the **New password** field, enter a new password. The password can be from 1 to 10 characters, including upper and lowercase letters and digits. It can be anything other than 0000.

4. In the **Confirm password** field, re-enter your password.

5. Click **Submit**.

   If the two passwords do not match, you receive a message that the password and confirmation do not match. Re-enter your password in both fields.

If you entered the new password correctly in both fields, the Main Menu page shown in Figure 72: User Main Menu page appears.


Nortel Reporting for Contact Center - Windows Internet Explorer
http://localhost/rcc2.5/main/main_index.asp
Nortel Reporting for Contact Center
NORTEL
Main
Logout
Help
v 2.5.412.0.61
Main Menu
Welcome Mary
From this screen you can navigate to the various areas of Reporting for Contact Center.
Help is available within each section from the help tab at the top of screen and you may log out at any time by pressing the log out button.
Real Time
Agent Alarms
Wallboard Setup
Time Bins Setup
Reports and Schedules
Done
Local intranet
100%

Figure 72: User Main Menu page

The page shown in Figure 72: User Main Menu page is the Main Menu for all regular (*non-Administrator*) Users. Note that the word Administrator is *not* displayed in the blue bar at the top of each page.

Also note that Nortel Reporting for Contact Center recognizes who logs on and greets the User accordingly. In the example shown in the figure, User Mary Smith logged on, and the page displays the Welcome Mary message.

The options available to Users appear in the navigation pane on the left of the Main Menu page.

The options are as follows:

- Real Time
- Agent Alarms
- Wallboard Setup
- Time Bins Setup
- Reports and Schedules

Real Time

From the User Main Menu page shown in Figure 72: User Main Menu page, select **Real Time** to view the Real Time page, shown in Figure 73: Real Time page.



Figure 73: Real Time page

Using the Real Time Options

To view the Real Time screens, the minimum screen resolution should be at least 1024 x 768 pixels.

> **Note**: The maximum recommended number of Client PC connections that can view all four Real Time screens concurrently at a one second refresh rate are 4 PCs. At a three second refresh rate up to 12 PC's can view all four Real Time screens concurrently.

Perform the following steps to use the Real Time options:

1. To select the Real Time screens you want to view, select a Real Time screen name.

- For information about using Skillset selection lists, see page 141.
- For information about using Favorites, see page 141.

2. Click **Submit** to view your Real Time selections in a new window. To reset your selections, click **Cancel** at any time.

Note: A Java coffee cup icon will appear in the bottom left hand side of the screen (beneath the menu) displaying the version of the Java Runtime Environment (JRE) installed on the PC (or the version being should there be multiple JRE installations). If this is not displayed you will automatically be presented with an option to download and install the JRE, in addition the submit button will also not be displayed and you wont be able to launch any Real Time screens. Please follow the instructions on screen to successfully install the JRE.

The following sections describe the available Real Time screens:

Real Time Call Summary

Figure 74: Call Summary Real Time screens shows the Call Summary Real Time screen.


Nortel Reporting for Contact Center - Windows Internet Explorer
NORTEL
v 2.5.412.0.61
Call Summary
You are currently viewing Skillsets: SKILL1, SKILL2, SKILL3
Incoming Contact Center Calls
Skillset
Waiting
Delayed
Primary Alert
Secondary Alert
Overflow
Answered Hour
Answered Day
Abandoned Hour
Abandoned Day
Disconnected Hour
Disconnected Day
Longest Waiting Time
Unread Skillset Mailbox Msgs
Service Level
Skillset Mode
Grouping 0 0 0 0 0 0 0 0 0 0 0 00:00:00 0 100%
1 SKILL1 0 0 0 0 0 0 0 0 0 0 0 00:00:00 0 100% Day
2 SKILL2 0 0 0 0 0 0 0 0 0 0 0 00:00:00 0 100% Day
3 SKILL3 0 0 0 0 0 0 0 0 0 0 0 00:00:00 0 100% Day
Connection Status

Figure 74: Call Summary Real Time screens

The information in the Call Summary screen updates as call activity changes in your Contact Center. Each row in each screen represents a single Skillset. The Skillsets that you see are the skillsets you selected on the Real Time page shown in Figure 73: Real Time page.

The summary provides information about calls that are in the Skillset queues waiting to be answered, together with some statistics regarding calls that are completed. These statistics update in real time.

The following sections describe the available information for each of the selected Skillsets.

Waiting

Waiting indicates the number of calls that are currently waiting in the Skillset queues to be answered.

Delayed

Delayed indicates the number of calls that are currently in a delayed state, that is, having reached the contact center but have not been forwarded to a skillset.

Primary Alert

Primary indicates the number of currently waiting Calls that have waited in excess of the Contact Center Primary Alert. (Note that this is mutually exclusive with the Secondary Alert). If any calls have waited in excess of the Primary Alert, the background to this cell changes to yellow.

Secondary Alert

Secondary Alert indicates the number of currently waiting Calls that have waited in excess of the Contact Center Secondary Alert. (Note that this is mutually exclusive with the Primary Alert). If any calls have waited in excess of the Secondary Alert, the background to this cell changes to red.

Overflow

Overflow indicates the number of currently waiting Calls that have waited in excess of the Contact Center Overflow Threshold. Note that this does not mean the call has overflowed, but the Contact Center is actively looking through the overflow rules that have been defined for this Skillset to find a means of answering the call. That is, this call is liable to overflow shortly. If any calls have waited in excess of the Overflow Threshold, the background to this cell changes to red.

Note: If a call had passed the overflow threshold in one Skillset and was then moved to another Skillset due to the call routing that was configured, the call appears in the new Skillset. The cell background will be red because this call has already passed the overflow threshold of its original Skillset.

Abandoned Hour/Day

Abandoned Hour/Day indicates the number of calls that were abandoned in the Skillsets, in the current hour and in the current day.

Answered Hour/Day

Answered Hour/Day indicates the number of calls that were answered by the Agents in the Skillsets, in the current hour and in the current day.

Disconnected Hour/Day

Disconnected Hour/Day indicates the number of calls that were disconnected by the call center in the current hour and in the current day.

Longest Waiting Time

Longest Waiting Time indicates the waiting time of the call that has waited the longest, of the list of currently waiting calls.

Unread Skillset Messages

Indicates the number of voice mail messages in the Skillset Mailbox which have not be listened to. If any messages have not been listened to, the cell background is red.

Service Level

Indicates the level of service currently offered to incoming callers.

Skillset Mode

Indicates whether the mode of operation of the Skillset.

Grouping

The first row in the Call Summary Real Time screen is labeled Grouping. This row shows values generated from the data presented for each of the included skillsets. Note that the values might not include all the skillsets in the System because the User viewing the Call Summary screen might not be assigned all the skillsets, or they may be viewing only a selection of their assigned skillsets.

The Service Level figure in the Grouping row is a means average of the Service Level values of the skillset rows displayed below the Grouping row.

For example, three skillsets are in the view, and they had the following individual skillset values:

Skill 1 Service Level = 0%

Skill 2 Service Level = 100%

Skill 3 Service Level = 100%

The Grouping row shows a Service Level of 66%, calculated as follows:

Service Level = (0 + 100 + 100) / 3 = 66%

This value shows the User what their average Service Level is over all the selected skillsets. This figure is different from the Service Level for the System (which includes all the skillsets). The System Service Level is **not** calculated as an average for the skillsets; it is calculated as a single figure Service Level for the System.

This is the calculation that is used in the System wallboard parameters SH and SD and in the Call Detail real time. In the Call Detail Real Time screens and in the System SH and SD wallboard fields, the Service Level is calculated using the following formula: (This formula is also described in the Glossary on page 173)

```
Presented     = Total Number of Direct Call transactions
                Presented to the Skillset(s)
Abandoned     = Calls which Abandoned
>Secondary    = Calls transactions answered after the
                Secondary Alert has elapsed

                    Presented – Abandoned – >Secondary
Service Level % = ------------------------------------ x 100
                                Presented
```

Real Time Agent Summary

Figure 75: Agent Summary Real Time screen shows the Agent Summary Real Time screen.


Nortel Reporting for Contact Center - Windows Internet Explorer
NORTEL
v 2.5.412.0.61
Agent Summary
You are currently viewing Skillsets: SKILL1, SKILL2, SKILL3
Skillset
Logged In
Supervising
Available
Not Ready
Not Available
Ringing
On Contact Centre Calls
Break Time
On Non-Contact Centre Calls
On Outgoing Call
On Internal Call
With all Calls Held
Grouping 2 1 1 0 0 0 0 0 0 0 0 0
1 SKILL1 2 0 1 0 0 0 0 0 0 0 0 0
2 SKILL2 0 0 0 0 0 0 0 0 0 0 0 0
3 SKILL3 0 0 0 0 0 0 0 0 0 0 0 0
Connection Status

Figure 75: Agent Summary Real Time screen

The information shown in the Agent Summary screen updates as Agent activity changes in your Contact Center. Each row in each screen represents a single Skillset. The Skillsets that displayed are the skillsets selected on the Real Time page, as shown in Figure 73: Real Time page.

This Real Time screen indicates the numbers and states (current activities) of the logged-in Agents, for each of the selected Skillsets.

Note: The state of an Agent who has multiple calls on their handset is taken from their active call. For example, if an Agent has an Incoming Contact Center Call on hold and they are active on an Outgoing Call, then the Agent is shown to be in the Outgoing Call state. The following sections describe the available information.

Skillset

Indicates which Skillset the information in this row represents.

Logged In

Logged In indicates the number of Agents who are logged into this Skillset.

Supervising

Supervising indicates the number of Agents (Supervisors) who are currently supervising other Agents.

Available

Available indicates the number of Agents who are Available to take Incoming Contact Center Calls.

Not Ready

Not Ready indicates the number of Agents who are in the Not Ready State. They might have invoked the Make Not Ready feature. Or they might have been placed in the Not Ready state because a Contact Center Call was presented ringing to their handset but the Agent did not answer it, and Nortel Reporting for Contact Center automatically took the call back to the Skillset queue and made them Not Ready.

Not Available

Not Available indicates the number of Agents who are in the Not Available State. An agent may enter the Not Available state through actions like F981 voice mail, lifting the receiver (while not answering a call) and any other action that removes their ability to receive a call.

Ringing

Ringing indicates the number of Agents who have calls currently ringing on their handset.

On Contact Center Calls

On Contact Center Calls indicates the number of Agents who are currently handling Incoming Contact Center Calls.

Break Time

Break Time indicates the number of Agents who are in Break Time following clear down of an Incoming Contact Center Call.

On Non-Contact Center Calls

On Non-Contact Center Calls indicates the number of Agents who are currently handling calls that have not arrived through the Contact Center. These calls could be calls that arrived directly at their handset because someone rang their Direct Inward Dialing (DID) line, for example, or a non-Contact Center Call was transferred to them from another handset.

On Outgoing Calls

On Outgoing Calls indicates the number of Agents who are currently on Outgoing Calls.

On Internal Calls

On Internal Calls indicates the number of Agents who have placed or answered internal (intercom) calls.

With All Calls Held

With All Calls Held indicates the number of Agents who have all of their current calls on hold.

Real Time Call Detail

Figure 76: Real Time Call Detail Screen shows the Call Detail screen.



Figure 76: Real Time Call Detail Screen

The Call Detail Real Time screen presents a detailed display of the status of waiting calls together with statistics relating to completed calls. These statistics update in real time.

The screen displays a separate line of information for Multimedia Calls and for Voice (Public Switched Telephone Network (PSTN)) Calls and a total for both types of calls. The following sections describe the available information.

Media Type

Media Type indicates whether the line of statistics relates to Multimedia Call or Voice (PSTN) Calls or a total for both types of call.

Waiting

Waiting indicates the number of calls that are currently waiting in the Skillset queues to be answered.

Delayed

Delayed indicates the number of calls that are currently in a delayed state that is having reached the contact center but have not been forwarded to a skillset.

Primary Alert

Primary Alert indicates the number of currently waiting Calls that have waited in excess of the Contact Center Primary Alert. (Note that this is mutually exclusive with the Secondary Alert). If any calls have waited in excess of the Primary Alert, the background to this cell changes to yellow.

Secondary Alert

Secondary Alert indicates the number of currently waiting Calls that have waited in excess of the Contact Center Secondary Alert. (Note that this is mutually exclusive with the Primary Alert.) If any calls have waited in excess of the Secondary Alert, the background to this cell changes to red.

Overflow

Overflow indicates the number of currently waiting Calls that have waited in excess of the Contact Center Overflow Threshold. Note that this does not mean the call has overflowed, but the Contact Center is actively looking through the overflow rules that were defined for this Skillset to find a means of answering the call. That is, this call is likely to overflow shortly. If any calls have waited in excess of the Overflow Threshold, the background to this cell changes to red.

Note that if a call had passed the overflow threshold in one Skillset and was then moved to another Skillset due to the call routing that was configured, the call appears in the new Skillset and the cell background is red because this call has already passed the overflow threshold of the original Skillset.

Abandoned Hour/Day

Abandoned Hour/Day indicates the number of calls that were abandoned in the Skillsets, in the current hour and in the current day.

Answered Hour/Day

Answered Hour/Day indicates the number of calls that were answered by the Agents in the Skillsets, in the current hour and in the current day.

Disconnected Hour/Day

Disconnected Hour/Day indicates the number of calls that were disconnected by the call center in the current hour and in the current day.

On Hold

Indicates how many calls are placed on hold.

Longest Waiting Time

Longest Waiting Time indicates the waiting time of the call that has waited the longest, of the list of currently waiting calls.

Unread Skillset Mailbox Msgs

Indicates the number of voice mail messages in the Skillset Mailbox that have not be listened to. If any messages have not been listened to, the cell background is red.

Service Level

Service Level indicates the level of service being offered to incoming callers. The higher the value, the better the service.

Real Time Agent Detail

Figure 77: Agent Detail Real Time shows a detailed display of the individual status of the logged-in Agents, together with statistics relating to calls answered and made by the Agents. These statistics update in real time.



Figure 77: Agent Detail Real Time

Each line of the Agent Detail Real Time screen represents a single Agent.

The following sections describe the available information.

ID

Indicates the Contact Center ID of the Agent.

Agent and Status

The Agent column displays the agent name and indicates the state the agent is in by coloring the cell background. The state of the agent depends on their current activity.

Further detail on the Agent state is provided in the Status column, as follows:

- Available

  These are agents who are available to answer incoming Contact Center calls.

  Blue represents Available agents, as shown in Figure 78: Available state.

  The word **Available** is displayed in the Status column.

ID	Agent	Logged in SS	Status	Duration	Answered Contact Centre Calls		Outgoing Calls		Non-Contact Centre Calls	
					Hour	Day	Hour	Day	Hour	Day
2	Agent2	Multi	Available	00:01:00	1	2	0	0	0	0

Figure 78: Available state

- Break Time

  Break Time is the term used to describe the period of time allocated to each agent to allow post-call completion work, also called *Wrap-up*.

  Break Time is represented by dark green, as shown in Figure 79: Break Time.

  The wording **Break Time** is displayed in the Status column.

ID	Agent	Logged in SS	Status	Duration	Answered Contact Center Calls		Outgoing Calls		Non-Contact Center Calls	
					Hour	Day	Hour	Day	Hour	Day
2	Agent2	Multi	Break Time	99:05:14	0	0	0	0	0	0

Figure 79: Break Time state

- All Calls Held

  All Calls Held is the state when an agent has placed all of their calls on hold.

  All Calls Held is represented by pink, as shown in Figure 80: All Calls Held state.

  The wording **Calls Held** is displayed in the Status column.

ID	Agent	Logged in SS	Status	Duration	Answered Contact Centre Calls		Outgoing Calls		Non-Contact Centre Calls	
					Hour	Day	Hour	Day	Hour	Day
3	Agent3	Multi	Calls Held	00:00:24	1	2	0	0	0	0

Figure 80: All Calls Held state

- Incoming

  An agent is in the Incoming state when they have answered an Incoming Contact Center call.

  The Incoming state is represented by light green, as shown in Figure 81: Incoming (PSTN) state.

  The information in the Status column indicates the type of call this is, that is, a voice (PSTN) call.

  A phone icon in the Status column represents the voice call. This is accompanied with the skillset associated with the call, in the format **SS *n***, where *n* is the number of the skillset. For example, **SS 2** which represents Skillset 2.

ID	Agent	Logged in SS	Status	Duration	Answered Contact Centre Calls		Outgoing Calls		Non-Contact Centre Calls	
					Hour	Day	Hour	Day	Hour	Day
1	Agent1	1	☎ SS 1	00:00:25	1	1	0	0	0	0

Figure 81: Incoming (PSTN) state

- Incoming Non-Contact Center

  If an agent answers a non-Contact Center call, that is, where the agent's DN is dialled directly, they are represented by dark green.

  The Incoming non-CC state is shown in Figure 82: Incoming Non-CC state.

  The wording **Incoming non CC** is displayed in the Status column.

ID	Agent	Logged in SS	Status	Duration	Answered Contact Center Calls		Outgoing Calls		Non-Contact Center Calls	
					Hour	Day	Hour	Day	Hour	Day
1	Agent1	Multi	Incoming non CC	00:00:21	0	0	0	0	2	2

Figure 82: Incoming Non-CC state

- Intercom

  An Intercom call, also known as an Internal call, is where another agent dials to the agent.

  The Intercom state is represented by grey, as shown in Figure 83: Intercom state.

  A phone icon in the Status column is displayed next to the word **Intercom** to represent the voice call.

ID	Agent	Logged in SS	Status	Duration	Answered Contact Centre Calls		Outgoing Calls		Non-Contact Centre Calls	
					Hour	Day	Hour	Day	Hour	Day
4	Agent4	Multi	☎ Intercom	00:00:39	0	0	0	0	0	0

Figure 83: Intercom state

- Multimedia

  A Multimedia voice or browser call is when an agent has received a Multimedia Contact Center call. This is represented by bright green, as shown in Figure 84: Multimedia state.

  Different icons are displayed in the Status column along with the skillset number to represent different Multimedia calls, as follows:

  - A globe icon accompanying the skillset number – this represents a Multimedia browser-only call. The skillset number is in the format **SS *n***, where *n* is the number of the skillset. For example, **SS 2** which represents Skillset 2.
  - A phone and a globe icon accompanying the skillset number - represents a Multimedia voice and browser call.

ID	Agent	Logged in SS	Status	Duration	Answered Contact Center Calls		Outgoing Calls		Non-Contact Center Calls	
					Hour	Day	Hour	Day	Hour	Day
3	Agent3	Multi	SS 2	00:00:21	0	0	0	0	2	2

Figure 84: Multimedia state

- Supervisory Monitoring

  When an agent who is created in the Contact Center as a Supervisor undertakes a monitoring session with another agent, they are represented by orange. See Figure 85: Monitoring state.

  A Supervisor can be in different Agent Status' in a Supervisory Monitoring session. The words displayed in the Status column are as follows:

  - **Asked** – when an agent presses F906 to request help from the supervisor.
  - **Helping** – from **Asked**, the supervisor presses **YES** on the handset to accept the agent request for help. The supervisor begins monitoring the agent and can either:
    - view the agent details of the call state they are in; or
    - join the call.
  - **Monitoring** – pressing F905.
  - **Observing** – from **Viewing**, enter the Agent ID of the agent to monitor. In the Observing state the supervisor can select different options on the handset to:
    - view the agent details of the call state they are in;
    - start to monitor the agent; or
    - join the call.
  - **Viewing** – from **Monitoring**, selecting the skillset of the agent to monitor.

ID	Agent	Logged in SS	Status	Duration	Answered Contact Centre Calls		Outgoing Calls		Non-Contact Centre Calls	
					Hour	Day	Hour	Day	Hour	Day
2	Agent2	Multi	Monitoring	00:00:02	1	2	0	0	0	0

Figure 85: Monitoring state

- Not Available

  Agents who are unavailable to answer Incoming calls are in the Not Available state.

  Gold represents Not Available agents, as shown in Figure 86: Not Available state.

  The wording **Not Available** is displayed in the Status column.

ID	Agent	Logged in SS	Status	Duration	Answered Contact Centre Calls		Outgoing Calls		Non-Contact Centre Calls	
					Hour	Day	Hour	Day	Hour	Day
3	Agent3	Multi	Not Available	00:00:03	1	2	0	0	0	0

Figure 86: Not Available state

- Not Ready

  An agent who is in the Not Ready state is represented by dark grey. See Figure 87: Not Ready state.

  The wording **Not Ready** is displayed in the Status column.

ID	Agent	Logged in SS	Status	Duration	Answered Contact Centre Calls		Outgoing Calls		Non-Contact Centre Calls	
					Hour	Day	Hour	Day	Hour	Day
2	Agent2	Multi	Not Ready	00:00:54	1	2	0	0	0	0

Figure 87: Not Ready state

- Outgoing Call

  When an agent makes an Outgoing call, the agent is in the Outgoing Call state.

  The Outgoing Call state is represented by yellow. See Figure 88: Outgoing Call state.

  A phone icon in the **Status** column accompanies the wording **Outgoing Call** to represent this voice call.

ID	Agent	Logged in SS	Status	Duration	Answered Contact Centre Calls		Outgoing Calls		Non-Contact Centre Calls	
					Hour	Day	Hour	Day	Hour	Day
2	Agent2	Multi	Outgoing Call	00:00:24	0	2	1	1	0	0

Figure 88: Outgoing Call state

- Ringing

  These are agents who currently have a call ringing at their handset.

  Purple represents the agent's Ringing state, as shown in Figure 89: Ringing state.

  The word **Ringing** is displayed in the Status column.

ID	Agent	Logged in SS	Status	Duration	Answered Contact Centre Calls		Outgoing Calls		Non-Contact Centre Calls	
					Hour	Day	Hour	Day	Hour	Day
3	Agent3	Multi	Ringing	00:00:03	0	1	0	0	0	0

Figure 89: Ringing state

Logged In SS

Indicates the Skillsets the Agent is currently logged in to. Either the skillset number is provided if the agent is logged in to one skillset, or **Multi** is displayed if the agent is logged in to more than one skillset.

Duration

Displays a timer that represents the time the Agent has spent in the current state. If the Agent has been in the current state for a period in excess of the associated Agent Alarm, the background of this cell turns red. See Agent Alarms.

Answered Call Center Calls Hour / Day

Answered Call Center Calls Hour/Day indicates the number of Contact Center Calls that this Agent has answered in the current hour and in the current day.

Outgoing Calls Hour / Day

Outgoing Calls Hour/Day indicates the number of Outgoing Calls that this Agent has made in the current hour and in the current day. This does not include internal calls.

Non-Contact Center Calls Hour / Day

Non-Contact Center Calls Hour/Day indicates the number of Non-Contact Center Calls that this Agent has conducted in the current hour and in the current day.

Check Agent Alarms

Click **Check Agent Alarms** to update any Agent Alarms that had been set through Reporting for Contact Center after the Agent Detail Real Time screen had been opened.

Agent Alarms

The Agent Alarms option allows you to set Real Time thresholds that operate with reference to the Contact Center activity of the Agents.

For example, you can specify average durations of Incoming or Outgoing calls, and Nortel Reporting for Contact Center will highlight Agents who have been on a call longer than the specified threshold.

From the User Main Menu page shown in Figure 72: User Main Menu page, select **Agent Alarms** to view the Agent Alarms page shown in Figure 90: Agent Alarms menu page.



Figure 90: Agent Alarms menu page

Select **Agent Alarm Setup** to view the Agent Alarm Setup Skillset selection page shown in Figure 91: Agent Alarms Setup page.

This page allows the User to select their assigned Skillsets for which they wish to establish the Agent Alarms settings.

In the example shown in Figure 91: Agent Alarms Setup page, the Skillset list shows the Skillsets that User Mary Smith selected.

In a previous example, User Mary Smith saved SKILL1 and SKILL3 to her favorites list and named the favorite Skill1&3. See Figure 120: Save Favorites page. To select these skillsets for Agent Alarms Setup, she selected Skill1&3 from her favorites list, and Nortel Reporting for Contact Center automatically selected the Skill1 and Skill3.

- For a discussion of using Skillset selection lists see page 141.
- For a discussion on using Favorites, see page 141.



Figure 91: Agent Alarms Setup page

When you select your Skillset, click **Assign values** to view the Agent Alarms Values page shown in Figure 92: Agent Alarms Values page.

The Agent Alarms Values page allows you to specify threshold values for the following Agent activities (also called Agent states):

Available	Agent is free to take a call
Internal Call	Agent is on an intercom call
Outgoing Call	Agent has placed a call to an external party
Incoming Contact Center Call	Agent has answered a Contact Center Call
Incoming Multimedia Call	Agent has answered a Multimedia Call Center Call
Incoming Non-Contact Center	Agent has answered a non-Contact Center Call from an external party
Not Ready	The Agent is in the Not Ready state



Figure 92: Agent Alarms Values page

Select the value for each Agent State. To save the Agent Alarms Values settings, click **Submit**. The Agent Alarms Setup page appears. See Figure 91: Agent Alarms Setup page.

To leave the Agent Alarms Values page without saving any changes, click **Cancel**. The Agent Alarms Setup page appears. See Figure 91: Agent Alarms Setup page.

Wallboard Setup

If your supervisor has assigned you the rights to the Wallboard Setup option (see Add Users), you can use the Wallboards option to assign wallboards to your assigned Skillsets. You can also configure the wallboards with features such as wallboard alarms and messages, schedules, and summaries.

If your Administrator has not assigned you the rights to assign wallboards, the Wallboard Setup option is unavailable on the User Main Menu page. See Figure 72: User Main Menu page.

Nortel Reporting for Contact Center can support both hardware and software IP-enabled wallboards. The wallboards that are supported are the *ip***View** Wallboards (hardware tri-color wallboards) and the *ip***View** SoftBoard (software-based personal wallboard). They are updated approximately every 1 (default) or 3 seconds depending on the settings on the Contact Center Connection page, see Contact Center Connection on page 60.

Message Formats

The information sent to the wallboards is in one of three different formats: Parameter Messages, Scrolling Messages, or Summary Messages. The following sections describe these message formats.

Parameter Messages

Parameter Messages are the regular display messages sent to the wallboard.

Parameter Messages show six statistical parameters, each of which appears beside a two-letter mnemonic abbreviation. (If the wallboard is configured to have a title, then only three parameters can be displayed.)

The following parameters are available for display on the wallboards:

ID	Number of Incoming calls received in the current Day
IH	Number of Incoming calls received in the current Hour
AD	Number of Abandoned calls in the current Day
AH	Number of Abandoned calls in the current Hour
OD	Number of Outgoing calls made in the current Day
OH	Number of Outgoing calls made in the current Hour
SD	Service Level offered in the current Day (%)
SH	Service Level offered in the current Hour (%)
AO	Number of Agents on Outgoing calls
AI	Number of Agents on Incoming calls
AA	Number of Agents Available to receive calls
AN	Number of Agents in the Not Ready state
AL	Number of Agents Logged in

QL	Current Queue Length – number of calls queuing for this Skillset
QT	Current Queue Time for the longest waiting Call for this Skillset measured in seconds.

On the wallboards, the numerical values are displayed in yellow, and the abbreviations are displayed in green.

If one of the parameter values has an associated Alarm threshold configured for it, it appears in red when the threshold is broached. An audible alert for alarms is optional, see page 108.

Scrolling Messages

The wallboards also support Scrolling Messages (also known as rolling messages). Scrolling Messages are either manually dispatched messages, Alarm messages, or Scheduled messages.

Scrolling messages move from right to left across the wallboard until the whole message has been displayed at least two times. An audible alert for scrolling messages is optional.

> **Note**: On the *ip***View** SoftBoard, the scrolling messages do not scroll; they are displayed in their entirety in a window, for the duration that it would take for that message to scroll at least two times on the hardware wallboard. Also note that the numerical parameter display is removed from *ip***View** SoftBoard's for the duration of the message display.
>
> **Note**: The User must ensure that spaces are placed at the end of each word when creating messages for the ***ip***View SoftBoard otherwise the full message can not display the full message if it is a long string of characters without any spaces.

Scrolling messages are displayed on the wallboards under the following three circumstances:

- A Contact Center statistic has entered an Alarm state (generating an Alarm message).
- A predefined time has arrived (generating a scheduled message).
- A User has generated and dispatched a message (Instant [manual] message).

Nortel Reporting for Contact Center can be configured to provide an audible alert for any of these scrolling messages.

A scrolling message can be up to 64 characters in length and can contain parameter values that are automatically replaced by the numerical equivalent when they are displayed.

For example, if a message contained the text:

There are (QL) calls waiting.…

The Contact Center statistic QL currently has a value of 4; the following message would be displayed:

There are 4 calls waiting.…

Alarm Messages

Nortel Reporting for Contact Center can be configured to automatically provide a scrolling text message when a parameter enters an Alarm condition by passing a defined Alarm Threshold.

A profile of six different Alarm Thresholds can be set across a day, for a single Alarm.

For example, a 24-hour Contact Center that has 25 Agents active during the day might have an Alarm Message set to be triggered if 6 Agents are Not Ready concurrently. At Night, however, the Contact Center has a staff of 4 Agents, and they want to have the same Alarm Message triggered when only 2 Agents make themselves Not Ready.

Alarm messages scroll at least twice on the wallboards. If the alarm is still valid when the message has scrolled at least twice, the normal numerical display is shown for 5 seconds before the alarm message is re-scrolled.

If several alarms are triggered at once they are scrolled to the wallboard as follows.

1. Assume three alarms are triggered concurrently. The first alarm message is scrolled at least twice, and then the normal numerical display is shown for 5 seconds. The second alarm message is then scrolled at least twice, and the normal numerical display is shown again for 5 seconds.
2. If the third alarm is still valid, then the third alarm message is scrolled at least twice and the display then returns to the usual numerical display for 5 seconds.
3. If the first alarm is valid, it is scrolled again. If it is not valid, then the second alarm is checked to see whether it is valid. If the second alarm is valid, it is scrolled again.
4. If it is not valid, then the third alarm is checked to see whether it is valid. In this way, all alarms are rotated and displayed with a numerical display of 5 seconds in between them.

Scheduled Messages

Wallboard Messages that need to go out at the same time every day or on a particular day can be associated with a schedule.

For example, weekly fire alarm tests or a start of shift greeting or an end of shift message could be configured so that they automatically trigger at the specified time.

Schedules can be configured to trigger on single days, groups of days, or every day.

Scheduled messages take priority over Alarm messages.

Instant Messages

System Administrators or Users can manually enter and dispatch an Instant Message to the wallboards. Instant messages take priority over Alarm messages.

Summary Messages

Nortel Reporting for Contact Center can be configured to provide predefined hourly summaries on the wallboards. Summaries can be configured to have an audible alert.

The values displayed in the summary messages are as follows:

- Incoming Calls for previous Hour and Day so far
- Outgoing Calls for previous Hour and Day so far
- Answered Calls for previous Hour and Day so far

- Service Level for previous Hour and Day so far

Using the Wallboard Options

To use the Wallboard Options, select **Wallboard Setup** from the User Main Menu page (see Figure 72: User Main Menu page). The Wallboard Menu page shown in Figure 93: Wallboard Menu page appears.



Figure 93: Wallboard Menu page

The Wallboard Setup options are as follows:

- Wallboard Assignment
- Messages
- Alarms
- Schedules
- Instant Messages

The following sections describe the Wallboard Setup options.

Wallboard Assignment

From the Wallboard Setup menu, select **Wallboard Assignment** option to view the Wallboard Assignment page shown in Figure 94: Wallboard Assignment page. This page displays a list of the configured wallboards. It displays the configured wallboards for each of the Skillsets you are assigned and any Skillsets that are configured as System wallboards.



Figure 94: Wallboard Assignment page

You can delete wallboards or edit their settings.

In the example shown above in Figure 94: Wallboard Assignment page there are no wallboards assigned to the selected Skillsets. In the example, User Mary Smith can only add wallboards.

Perform the following to add a wallboard:

1. Click **Add** to assign wallboards. The Add Wallboard page shown in Figure 95: Add Wallboard page appears.



Figure 95: Add Wallboard page

2. In the **IP/Network Name field,** enter the IP Address or Network Name. (If the wallboard is an *ip***View** SoftBoard, enter the IP Address or the Network Name of the PC on which the SoftBoard will be running.)

3. The value in the **Port** is usually left at the default value of 3500. This value might be changed for an *ip***View** SoftBoard if an Agent wishes to have several copies of *ip***View** SoftBoard running on the same PC to, for example, display different Skillset statistics to a multi-Skillset Agent. Each copy of *ip***View** SoftBoard would be installed on the Agent's PC with a different Port number. In that case, the corresponding wallboard entry in Nortel Reporting for Contact Center must be configured with the appropriate port number.

4. The **Wallboard Skillset** selection specifies the Skillset the wallboard is to report on. That is, the named Skillset is the Skillset from which Nortel Reporting for Contact Center extracts the statistical information to display on the wallboard. If you wish to display system-wide totals

(that is, to have the information displayed represent totals derived from all Skillsets) select **System** from the list.

In other words, assigning a wallboard to be a System wallboard causes Nortel Reporting for Contact Center to send statistics to that wallboard which represent the system totals. For example, the parameter AN (Agents Not Ready) on a System wallboard shows the total figure for the AN values of all Skillsets added together.

Notice that the only Skillsets available in this list are the ones that our example User Mary Smith was assigned by the Administrator.

5. In the **Language** list, select the language in which wallboard should be driven. Individual wallboards can be driven in any of the supported languages that appear in the list.

6. Select a **Type** option (Hardware or Software) to indicate whether the wallboard is a hardware wallboard or software SoftBoard. Any of the available parameters can be used on either the hardware or the software wallboards.

   The parameter spacing on the hardware wallboard allows for the display of two 3-digit and one 4-digit parameter per line, giving six parameters in total. The two parameters at the right hand end of the wallboard can display up to 4 digits at a time.

   Those parameters that are able to reach 4 digits cannot be configured for the positions that can display only 3 digits.

7. Select **Title** if the wallboard is to be configured with a title. A title is a string of text up to 16 characters in length, which is displayed on the top line of a hardware wallboard and above the parameter list on a SoftBoard. In both cases, the title reduces the number of parameters that can be displayed by the wallboard to 3.

8. If you selected **Title** in the previous step, enter the title in the **Title Text** field.

9. Select **Buzzer** if you want the wallboard to emit a short buzzing sound when a Summary Message or a Scrolling message is sent to it. If Buzzer is selected, you will also hear a buzzing sound when a parameter goes into alarm even if no Alarm Message is associated with the alarm (a static alarm).

10. Select **Summary** to send Hourly Summaries to the wallboard when each hour passes and when the Skillset enters Out Mode (that is, there are no Agents Logged In to the Skillset).

11. To save the changes, click **Submit**. The Wallboard Setup page appears, see Figure 96: Wallboard Setup page with a wallboard listed. As shown in the figure, after you assign a wallboard, the wallboard appears on the page.

    To leave the Add Wallboard page without saving any changes, click **Cancel**. The Wallboard Setup page appears.



Figure 96: Wallboard Setup page with a wallboard listed

Click **Edit** to view the Edit Wallboard page shown in Figure 97: Edit Wallboard page.



Figure 97: Edit Wallboard page

The Edit Wallboard page is set up exactly like the Add Wallboard page shown in Figure 95: Add Wallboard page, except the data fields are populated with the values of the wallboard you selected to edit.

To save the changes, click **Submit**. The Wallboard Setup page appears. See Figure 93: Wallboard Menu page.

To leave the Add Wallboard page without saving any changes, click **Cancel**. The Wallboard Setup page appears. See Figure 93: Wallboard Menu page.

Click **Parameters** to view the Edit Parameters page, shown in Figure 98: Edit Parameters page.



Figure 98: Edit Parameters page

The Edit Parameters page allows you to specify which six (or three, if you specified that the wallboard is going to have a title, as described on page 108) parameters are displayed on the wallboard.

The list of available parameters is shown on page 108. Select the parameters from the lists on the page.

Note: If the wallboard for which you are specifying parameters is a hardware wallboard, some parameters appear only in positions 3 and 6. The lists for positions 1, 2, 4, and 5 do not show those parameters because the parameters that are restricted to positions 3 and 6 are capable of displaying up to 4 digits. Positions 3 and 6 on the hardware wallboard are larger than positions 1, 2, 4, and 5. Any parameter can occupy any position on a software wallboard.

When you have selected your parameters, click **Submit**. The Wallboard Setup page appears. See Figure 93: Wallboard Menu page.

To return to the Wallboard Setup page without saving any changes, click **Cancel**. You are prompted to confirm that you do not wish to save your changes.

Click **Delete** to remove the wallboard definition from the system and to remove its listing from the Wallboard Setup page.

You are prompted to confirm the deletion. After you confirm the deletion, the Wallboard Setup page appears. See Figure 93: Wallboard Menu page.

Messages

The Messages option allows you to create and store messages that can be used as Alarm or Scheduled messages.

Select the Wallboard Setup **Messages** option to view the Assigned Messages page shown in Figure 99: Assigned Messages page. This page lists all the messages that are configured. Any message can be used by any Skillset.

Initially, the list of Assigned Messages is empty (as shown in Figure 99: Assigned Messages page).



Figure 99: Assigned Messages page

Click **Add** to view the Add Messages page shown in Figure 100: Add Message page.



Figure 100: Add Message page

Type your message text in the blank field.

Note that if you include a parameter abbreviation in round brackets ‘(’ and ‘)’ in the text of the message, the appropriate numerical value of that Contact Center statistic replaces the parameter abbreviation when the message is displayed.

See the list of available parameters on page 108, and the discussion of parameter abbreviations being replaced with numerical values on page 103.

Figure 101: Add Message page – example text shows an Add Message page with a message example.



Figure 101: Add Message page – example text

In the example, User Mary Smith entered the following message in the Add Message text field:

There are (AN) Agents Not Ready please return to available

The parameter abbreviation AN represents Agents Not Ready. When this message is displayed on a wallboard the current numerical value of "AN" is inserted in the message instead of the (AN) symbol.

If there are 6 Agents Not Ready at the time the message was displayed on the wallboard, the following text is displayed:

There are 6 Agents Not Ready please return to available

Click **Submit** to save the message text you typed. The Assigned Messages page shown in Figure 102: Assigned Messages list – example messages appears.

To leave the Add Messages page without saving any changes, click **Cancel**. The Assigned Messages page shown in Figure 102: Assigned Messages list – example messages appears.



Figure 102: Assigned Messages list – example messages

User Mary Smith clicked **Submit** to save her new message. Her Assigned Messages List now includes the message she saved, as shown in the example.

Mary Smith also entered a message that will be used in a schedule. This message is a text message only and does not include any parameter abbreviations. This message will be use later in a Schedule.

The text of the other message is:

Morning Shift Logout, Afternoon shift Login

After messages are assigned to these Skillsets, they can be used in Alarms or Schedules.

You can use the **Edit** button to edit the details of a message, and you can use the **Delete** button to remove a message from the list.

Alarms

Select the Wallboard Setup **Alarm** option to view the Assigned Alarms page shown in Figure 103: Assigned Alarms page.



Figure 103: Assigned Alarms page

The Assigned Alarms list is empty initially.

To create an Alarm, click **Add**. The Add Alarm page shown in Figure 104: Add Alarm page appears.



Figure 104: Add Alarm page

Follow these steps to specify an alarm:

1. In the **Wallboard Skillset** list, select a skillset that is specific to the alarm.

   Note: When you assign an Alarm, the alarm is specific to a particular Skillset (or the System, if you select the System list item). An *Alarm Message* can be used by many Skillsets, but an *Alarm* is specific to a single Skillset.

2. In the **Parameter name** list, select the alarm parameter that triggers the alarm. Refer to the list of available parameters on page 108.

   Note: You can specify the same alarm conditions for different Skillsets, and these different alarms can use the same Alarm message, but they are separate and distinct alarms, and they must be created separately.

   Note: If you configure an Alarm to be a System Alarm, the Alarm appears on all wallboards that have been configured as System wallboards. You can specify the same alarm conditions for different Skillsets, and these different alarms can use the same Alarm

message, but they are separate and distinct alarms, and they operate independently, with no interaction.

3. In the **Period Start Time** list, specify the start time for the period of the day in which the Alarm is operational. For more information, refer to Alarm Periods.

   Note: Alarm Periods allow you to specify different Thresholds, Comparisons, and Messages for different periods of the day, for a single Alarm. An Alarm period is in operation after its start time has passed and before the start time of the next period has been reached.

   You can specify different Alarm conditions for a single Alarm for up to six Alarm Periods throughout a single day. To define an Alarm Period, specify the start time for that period.

   If only one Alarm Period is configured, that Alarm Period is in operation 24 hours a day.

4. In the **Comparison** list, select the type of comparison that determines if the alarm condition is triggered. The types of comparisons are as follows:

   <= Less than or equal to. Use this type of comparison to monitor a parameter against some lower limit. That is, you wish to be informed if the parameter value ever drops to or decreases below the Threshold you supply. For example if you wish an alarm to be triggered if the Service Level for the Current Hour (SH) falls below 50, you would use SH <= 50.

   = Equals. Use this type of comparison to monitor a parameter against an exact figure. That is, you wish to be informed if the parameter value ever exactly matches a figure, perhaps a target. Note that in this type of comparison, if the parameter value is higher than the threshold, the alarm condition is not triggered. The parameter must exactly match the threshold in order to trigger the alarm. For example, you may wish to have a congratulatory message sent to the wallboards if you exceed your highest number of incoming calls for the day. If your highest number of incoming calls for the day was 1200, you could set an Alarm for the parameter ID. However, if you use ">= ", the Alarm would be triggered for each and every call from 1200 on. Instead, you would use the format ID = 1201. This means that the alarm message will be sent *only* when the number of incoming calls in the day equals 1201 (one higher than your previous highest total). This avoids the message being repeatedly sent as calls continue to come in and the ID figure rise. (At the end of that day, you would then note your n highest ID figure and edit the Alarm to reflect your new record Incoming Calls in the Day total.)

   >= Greater than or equals to. Use this type of comparison to monitor a parameter against some upper limit. That is, you wish to be informed if the parameter value ever meets the Threshold you supply. For example, if you wish an alarm to be triggered if the number of Agents who have made themselves Not Ready rises above 4, you would use AN >= 4.

5. In the **Threshold** field, enter a numerical threshold against which the parameter value is compared. Nortel Reporting for Contact Center automatically understands whether the figure you supply represents:

   - Agents (for parameters such as AN and AO)
   - Calls (for parameters such as ID and OD)
   - Seconds (for parameters such as QT)
   - Percentages (for parameters such as SD)

6. In the **Message** list, select the message that is sent when the alarm is triggered.

   Note: A Static Alarm does not have an alarm message. In the case of a Static Alarm, the parameter value is displayed in flashing red on the wallboard. For this type of Alarm to be effective, the parameter must be one of the parameters you chose to have displayed on your wallboard (see **Parameters** button on page 110). To specify a Static Alarm, select **No Message** from the Message list.

Alarm Periods

You can specify different Alarm conditions for a single Alarm for up to six Alarm Periods throughout a single day. You define the Alarm Periods by specifying start times for each period. Alarm Periods allow you to specify different Thresholds, Comparisons, and Messages for different periods of the day, for a single Alarm. An Alarm period is in operation when its start time has passed and before the start time of the next period has been reached.

Note: If only one Alarm Period is configured, then that Alarm Period is in operation 24 hours a day.

In the example shown in Figure 105: Example Settings for a Multi Alarm Period Alarm, User Mary Smith configured an Alarm with three time periods for one of her Skillsets.



Figure 105: Example Settings for a Multi Alarm Period Alarm

The Alarm is triggered when the parameter AN (number of Agents Not Ready) passes beyond the thresholds.

The Skillset applies to three shifts of Agents: a morning shift, the evening shift, and the late shift, which consists of a smaller number of Agents.

Because the Skillset has a different number of Agents Logged in during each shift, an Alarm based on Agents Not ready must have different thresholds to allow for the different numbers of Agents Logged in at the various periods throughout the 24-hour cycle.

In the example shown in Figure 105: Example Settings for a Multi Alarm Period Alarm, the first Alarm Period begins at 08:30 in the morning. The comparison is “>= “, so the Alarm is triggered when the AN parameter meets or exceeds the threshold. The threshold is 5. When the AN parameter reaches 5 or above, the selected message is sent to the wallboards that are assigned to this Skillset.

The second Alarm Period begins at 17:30 in the evening. The comparison is ">=", so the Alarm is triggered when the AN parameter meets or exceeds the threshold. The threshold is 3. When the AN parameter reaches 3 or above, the selected message is sent to the wallboards that are assigned to this Skillset. Because there are fewer Agents in the Afternoon Shift, the threshold is lowered to 3.

The third Alarm Period begins at 22:30. Note that this Alarm Period operates until the next Alarm Period starts, which in this example is Alarm Period One, at 08:30 the following morning. Because of the smaller staff in Mary Smith's Skillset during the late shift, the Threshold is lowered to 2.

In all cases, the same Alarm Message is used. Because the (AN) symbol is replaced by the appropriate value of the AN parameter when the message is displayed (which is when the Alarm is triggered), a single message can be flexible enough to be used in different situations.

However, if Mary Smith wants to, she can use a different message for each Alarm Period, or she can configure any of the Alarm Periods to use a Static Alarm.

7. Click **Submit** to save your settings. The Assigned Alarms page shown in Figure 106: Assigned Alarms page with an alarm configured appears. Click **Cancel** to view the Assigned Alarms page without saving your changes.



Figure 106: Assigned Alarms page with an alarm configured

Schedules

Schedules allow you to automatically send a message to the wallboards of a Skillset (or the System) at a pre-defined time on a specified day or range of days.

Select the Wallboard Setup **Schedule** option to view the Assigned Schedules page shown in Figure 107: Assigned Schedules page.



Figure 107: Assigned Schedules page

The Assigned Schedules page displays a list of the assigned Schedules. Initially, this list is empty.

Click **Add** to create a new Schedule. The Add Schedule page shown in Figure 108: Add Schedule page appears.



Figure 108: Add Schedule page

Follow these steps to configure the Schedule:

1. In the **Wallboard Skillset** list, select a skillset that is specific to the schedule.

   Note: When you add a schedule, the alarm is specific to a particular Skillset (or the System, if you select the System list item). A *Schedule Message* can be used by many Skillsets, but a *Schedule* is specific to a single Skillset.

.

   Note: If you configure a Schedule to be a System Schedule, that Schedule appears on all wallboards that are configured as System wallboards.

   Note: You can specify the same Schedule settings for different Skillsets, and these different Schedules can use the same Schedule message, but they are all separate and distinct Schedules, and they must be created separately.

2. From the **Day** list, select the day on which the Schedule operates. You can set a Schedule to operate on a specific day of the week, every day from Monday to Friday, every day from Monday to Saturday, or Daily (every day).

3. From the **Time** list, select the time, in hours and minutes, that the Schedule is triggered.

   Note: The **Time** list uses the 24-hour clock.

   Our example User Mary Smith has created a schedule which will operate on each day of the working week, Monday to Friday

4. From the **Message** list, select the message to send at the specified time on the specified range of days. The list includes all messages that are assigned to this skillset.

5. Click **Submit** to save your changes. The Assigned Schedules page shown in Figure 109: Assigned Schedules page with schedule added appears. Click **Cancel** to leave the Add Schedules page without saving your changes.



Figure 109: Assigned Schedules page with schedule added

The example Assigned Schedules page shows the newly created Schedule. As shown in the example, Mary Smith wants the *Morning Shift Log Out, Afternoon Shift Login* message sent to the Skillset 3 wallboards at 13:00, each day of her working week, which runs from Monday to Friday.

Click **Edit** to change any details of a Schedule. The Edit Schedule page shown in Figure 110: Edit Schedule page appears.



Figure 110: Edit Schedule page

This Edit Schedule page is set up exactly like the Add Schedule page shown in Figure 108: Add Schedule page.

Click **Submit** to save your edits. The Assigned Schedule page shown in Figure 109: Assigned Schedules page with schedule added appears.

Click **Cancel** to leave the Edit Schedules page without saving any edits. The Assigned Schedule page shown in Figure 109: Assigned Schedules page with schedule added appears.

Instant Messages

Instant messages allow Users to manually select any one of the stored wallboard messages and to send them to the wallboards at will.

Users can also type any text and have it sent to the wallboards, for one-off requirements. These messages are sent to the wallboards and then discarded. They are not saved. If you wish to save a message, use the Wallboard Message options on page 112 to add the message to the list of stored messages.

Select Wallboard Setup **Instant Messages** option to view the Instant Messages page shown in Figure 111: Instant Messages page.



Figure 111: Instant Messages page

From the Instant Messages page, you can select the Skillsets to which you wish to dispatch the instant message. The available Skillsets are those that your Administrator assigned to you.

- For more information about using Skillset selection lists see page 141.
- For more information about using Favorites, see page 141.

In the example shown in Figure 111: Instant Messages page, User Mary Smith used her Skill1&3 Favorite to select the Development and Training Skillsets.

Click **Instant Messages** to view the Instant messages page that allows you to compose an instant message. See Figure 112: Composing an Instant Message.



Figure 112: Composing an Instant Message

You can send an existing stored message or create a new message.

Follow these steps to create and send an Instant Message.

1. To send an existing message, select the stored message from the **Existing** messages list. To create a new message, type the new message in the **New Message** field.

.

2. Click **Send** to send the message to the wallboards.

   - If the New message field does not contain any text, the displayed message in the Existing messages list is sent to the wallboards.
   - If the New message field contains text, that text is sent to the wallboards.

   In either case, the **Instant Messages** page appears after you click Send.

   Click **Cancel** to return to the Instant Messages page without sending an Instant Message.

   Note: You can include parameter abbreviations in brackets in the text of the new message. When the message is displayed, the abbreviations are replaced with the correct numerical value for the parameter. (For more information about parameter substitution, refer to page 103.)

Time Bins Setup

The Time Bins option allows you to specify the settings for the Answer and Abandon Time Bins for the Skillsets that are assigned to you. Answer and Abandon Time Bins are collectively known as the Time Bins.

Answer Time Bins

The Answered Time Bins are a series of six time steps used in the statistical analysis of Answered Calls. Nortel Reporting for Contact Center provides statistical reports on the percentage of incoming calls answered within each of the periods specified in the chosen Answered Time Bins.

A seventh Answer period is also used in the reports. The seventh period gathers information about all calls that are answered *after* the period specified by the sixth Answered Time Bin.

Abandon Time Bins

The Abandon Time Bins are a series of six time steps used in the statistical analysis of Abandoned Calls. Nortel Reporting for Contact Center provides statistical reports about the percentage of incoming calls abandoned within each of the periods specified in the chosen Abandoned Time Bins.

A seventh abandoned period is also used in the reports. The seventh period gathers information about all calls that are abandoned *after* the period specified by the sixth Abandoned Time Bin.

Note: If other Users have been assigned these Skillsets, they can change these settings.

Select the **Time Bins Setup** option to view the Time Bin Setup page, shown in Figure 113: Time Bin Setup Skillset selection page.



Figure 113: Time Bin Setup Skillset selection page

The Time Bin Setup Skillset selection page allows you to select a Skillset for which you wish to set Time Bin values. Note that the list of available Skillsets in Figure 113: Time Bin Setup Skillset selection page contains only those Skillsets that the Administrator assigned to the User.

Follow these steps to set Time Bin values for Skillsets.

1. In the **Skillsets** list, click any Skillsets to select the Skillset for which you wish to set the Time Bin values.
2. Click **Assign Time Bins**. The Time Bins values page shown in Figure 114: Time Bins page appears.



Figure 114: Time Bins page

3. In the **Answered Time Bins** and **Abandoned Time Bins** lists, enter the time required to define the periods into which you wish to have calls that are answered or abandoned in these Skillsets categorized.

   The steps in the Time Bin periods need not be the same, but you must set the Time Bin periods in ascending order.

   For example, if you want to have Nortel Reporting for Contact Center report on Answered calls, grouping together the calls that were answered within 10 seconds, the calls that were answered between 10 and 20 seconds, the calls that were answered between 20 and 30 seconds, the calls that were answered between 30 and 40 seconds, the calls that were answered between 40 and 50 seconds, the calls that were answered between 50 seconds and one minute, you would set the Time Bins as 00:10, 00:20, 00:30, 00:40, 00:50, and 01:00.

   Note that Nortel Reporting for Contact Center also includes a category for anything greater than the last time period, which in this example would be ‘anything answered after 01:00’.

4. Click **Submit** to save your settings.

   To close the Time Bins page without saving your changes, click **Cancel**. The Time Bin Setup page shown in Figure 113: Time Bin Setup Skillset selection page appears.

Schedules

You can configure Print Schedules so that Nortel Reporting for Contact Center automatically prints a set of requested reports at a specified time. You can specify Print Schedules to print Daily, Weekly, or Monthly reports.

You can configure multiple Daily, Weekly, and Monthly Schedules.

For example, you may wish to print a set of reports each day before you arrive at your desk. In this case, you configure a Daily Schedule which prints at, for example, 08:00.
You can also have a different Daily Schedule report that refers to Agent Activity. You can configure Nortel Reporting for Contact Center to print these reports at, for example, 16:30 so that you can review the reports before the end of the day.

> **Note:** If the Web Host PC is powered off over the period in which the Schedule print is due to take place, the Schedule Print not produced. You can obtain the same reports by using the Reports options**.** For more information, refer to Reports.

> **Note:** If you select the Agent Audit by Agent, Agent Average by Agent, Agent Profile by Agent, Agent Activity by Agent, Activity Code by Skillset, the Activity Code by Agent**,** or the Activity Code by Pegs Reports to be included in your Print Schedule, you are prompted for the Agents and/or the Activity Codes you wish to include in these Reports. These steps are described on pages 172 (Agent reports), 172 (Activity Code by Skillset), 172 (Activity Code by Agents) and 172 (Activity Code by Pegs).

From the User Main Menu page shown in Figure 72: User Main Menu page, select **Reports and Schedule** to view the Report's page shown in Figure 115: Reports and Schedules page. As shown in Figure 115: Reports and Schedules page, the Print Schedules options are as follows:

- Daily Schedules (see Daily Schedules)
- Weekly Schedules (see Weekly Schedules)
- Monthly Schedules (see Monthly Schedules)



Figure 115: Reports and Schedules page

Daily Schedules

Select **Daily Schedules** to view the **Your Daily Schedules** page, shown in Figure 116: Your Daily Schedules page. Initially the page does not display any schedules.



Figure 116: Your Daily Schedules page

Follow the steps in this section to add a Daily Schedule.

1. Click **Add**. The Add Daily Schedules page shown in Figure 117: Add Daily Schedule page appears.



Figure 117: Add Daily Schedule page

The Add Daily Schedule page allows you to specify which reports you wish to have included in the Schedule, which days are to be included in the Schedule, and when to print the reports.

2. To set a name for your Schedule, type the name in the **Schedule Name** field. This is to help you identify, and distinguish between, the different Schedules you create.

3. To select a report to be included in the Schedule, select the check box beside the report name. Each selected report has a check mark in the check box beside its name. You can select multiple reports.

4. To include the reports from a particular day in the Schedule, select the check box beside that day. You can select multiple days.

Note: Daily Reports print on the day following the day which is being reported. That is, if you select a Daily Report Schedule for Monday, it prints on Tuesday. This ensures that the report day has completely elapsed when the reports are generated.

5. To specify which printer generates the reports, select a printer name from the **Select printer** list. This list includes all the printers that are accessible from the Web Host PC. (The reports are generated from the databases held in the Web Host PC.)

6. The **Report Period Start Time** and **Report Period End Time** lists allow you to specify the period within each day for which the reports are generated. For example, if your Contact Center has a working day that starts at 08:30 and finishes at 17:30, you may wish to specify the Start Time as 08:00 (to see if you have early calls that you are missing by not having the Contact Center open) and 18:00 (to see if a late surge of calls occurs).

Figure 118: Add Daily Schedule page – example settings shows example settings that User Mary Smith configured for her Daily Schedule.



Figure 118: Add Daily Schedule page – example settings

Mary Smith selected the Answered Calls by Skillset, Abandoned Calls by Skillset and Abandoned CLID/DNIS reports to be printed at 08:30 each morning, for Monday through Friday. Her printouts will be generated on Tuesday for Monday, on Wednesday for Tuesday, and so on until Friday's reports are printed on Saturday morning.

Her schedule is called **AnswAband**, and the reports start to be generated at 08:30, on the Cannon iT5000-6000 PCL5e printer. The reports cover the period from midnight to midnight for each day.

7. To save your Daily Schedule, click **Submit**. The Daily Schedule Skillsets page, shown in Figure 119: Daily Schedule Skillsets page appears.

   To close the Add Daily Schedule page without saving your changes, click **Cancel**. The Your Daily Schedules page shown in Figure 116: Your Daily Schedules page appears.



Figure 119: Daily Schedule Skillsets page

The Daily Schedule Skillsets page allows you to select which Skillsets you wish to include in the generated reports that are produced by the Daily Schedule.

Skillset List Selection Methods

You can use the following techniques to select Skillsets from the Skillset List.

- Click an unselected Skillset name once to select it (it will be highlighted) and remove the highlight from any other currently selected Skillsets.
- Click a selected (highlighted) Skillset name once to unselect it. Note that if other Skillsets are selected and you click a Skillset name, you unselect all the other Skillsets.
- To select multiple Skillsets, press **Ctrl** and click on multiple Skillsets.
- Press and hold down the Shift key, then click a Skillset to select all the Skillsets between the currently highlighted Skillset and the Skillset you clicked.
- You can use **Select All** to select all the Skillsets at once.

Adding Selections to the Favorites List

If there are collections of the assigned Skillset for which you frequently need to review the Daily Schedules, you can add the selection of Skillsets to the Favorites list.

When you add the selection to the Favorites list, instead of having to select a particular collection of Skillsets each time you wish to use them, you can click **Select** beside the appropriate Favorite, and the collection of Skillsets is highlighted at once. You do not need to select a particular collection of Skillsets each time you wish to use them.

Follow these steps to add a Favorite to the Favorite List.

1. Select the Skillsets you wish to include in the Favorite List and then click **Create Favorite**. The Save Favorites page appears, as shown in Figure 120: Save Favorites page.



Figure 120: Save Favorites page

2. Enter a name in the **Favorite Name** field, and then click **Submit** to save the name. (Click **Cancel** to return without saving the Favorite.)

   In the example shown in Figure 120: Save Favorites page, Mary Smith created a favorite that contains the Skillsets SKILL1 and SKILL3 called “Skill1&3”. When a Favorite is created, it appears in the Favorite List at the top of the page.

   Note: Many pages within Nortel Reporting for Contact Center allow you to use S lists and Favorites, and the techniques described here apply also to all those other pages. All the Favorites you create are accessible from any point within Nortel Reporting for Contact Center that allows you to use Favorites.

   Mary Smith clicked Select beside her new Favorite (Skill1&3), and the two associated Skillsets are selected for her.

Saving your Daily Schedule

1. To save your Daily Schedule, click **Submit**. The Your Daily Schedules page shown in Figure 121: Your Daily Schedules with a Schedule in the List appears. The page shows the Daily Schedule that you created.

   To leave the Daily Schedule Skillsets page without saving any changes, click **Cancel**. The Your Daily Schedules page appears. See Figure 116: Your Daily Schedules page.

   Note: If you included the Agent Audit by Agent, Agent Profile by Agent, Agent Activity by Agent, Agent Average by Agent, Activity Code by Skillset, Activity Code by Agent, or the Activity Code Report by Pegs Reports in your Print Schedule, you are prompted for the Agents and/or the Activity Codes you wish to include in these Reports. These steps are described on pages 172 (Agent Reports), 172 (Activity Code by Skillset), 172 (Activity Code by Agents) and 172 (Activity Code by Pegs).



Figure 121: Your Daily Schedules with a Schedule in the List

Note that each Schedule can be identified by the Schedule Name that was provided when the Schedule was created.

.

Deactivate

Click **Deactivate** to disable the Print Schedule so that the schedule is no longer printed when the schedule is due to run. When a schedule is disabled, the button changes from Deactivate to Activate, and a red cross replaces the green check mark, similar to the following illustration.



Activate

Click **Activate** to enable the Print Schedule so that the schedule is printed when the schedule is due to run. Once a schedule is enabled, the button changes from Activate to Deactivate and a green check mark replaces the red cross, similar to the following illustration.



Edit

Click **Edit** to change the settings for a Schedule.
The Edit Daily Schedule page, shown in Figure 122: Edit Daily Schedules page appears.



Figure 122: Edit Daily Schedules page

This page is set up exactly like the Add Daily Schedule page, except the fields and check boxes are populated with the settings of the Schedule you are editing. In the example, you are editing the AnswAban schedule. Make any necessary changes and click **Submit**. Your Daily Schedules page appears. See Figure 121: Your Daily Schedules with a Schedule in the List

To leave the Edit Daily Schedule page without saving any changes, click **Cancel**. The Your Daily Schedules page appears. See Figure 121: Your Daily Schedules with a Schedule in the List.

Delete

Click **Delete** to remove the Schedule from the system and to remove its listing from the Your Daily Schedules page.

You are prompted to confirm the deletion. When you confirm the deletion, the Your Daily Schedules page appears

Weekly Schedules

On the Print Schedules page shown in Figure 115: Reports and Schedules page, select **Weekly Schedules** to view the Your Weekly Schedules page. See Figure 123: Your Weekly Schedules page. Initially, the page does not show any schedules.

The Add Weekly Schedule page allows you to specify which reports you wish to include in the Schedule and when to print the scheduled reports.

You can also specify which period of the day the reports contain. You must specify a name for your Schedule and the printer on which you wish to generate the reports.



Figure 123: Your Weekly Schedules page

Follow the steps in this section to add a Weekly Schedule:

1. Click **Add**. The Add Weekly Schedules page shown in Figure 124: Add Weekly Schedule page appears.



Figure 124: Add Weekly Schedule page

2. To set a name for your Schedule, enter the name in the **Schedule Name** field. The name helps you identify and distinguish between the different Schedules you create.

3. To select a report to include in the Schedule, click the check box beside the report name. Selected reports have a check mark in the check box beside their name. You can select multiple reports.

4. The reports are generated for a calendar week. From the list, select the day on which the Weekly Schedule reports are generated.

Note: Weekly Schedules generate reports on the specified day at the specified time. However, the generated reports contain information from the previous calendar week. For example, a User creates a Weekly Schedule to print on a Saturday. They create this Schedule on September 10th, 2003. See Figure 125: Calendar for September 2003. On Saturday September 13, the Weekly Schedule generates Weekly reports. These Reports contain information relating to the week September 1st –September 7th. Reports containing the information relating to the week September 8th – September 14th are printed on Saturday, 20 September, and so on.

September 2003

Mon	Tue	Wed	Thu	Fri	Sat	Sun
1	2	3	4	5	6	7
8	9	10	11	12	13	14
15	16	17	18	19	20	21
22	23	24	25	26	27	28
29	30					

Figure 125: Calendar for September 2003

5. In the **Select printer** list, select the printer on which the reports will be generated. This list includes all the printers that are accessible from the Web Host PC. (The reports are generated from the databases held in the Web Host PC.)

6. In the **Report Period Start Time** and **Report Period End** Time fields, specify the period in each day for which the reports are generated. For example, if your Contact Center has a working day that starts at 08:30 and finishes at 17:30, you may wish to specify the Start Time as 08:00 (to see if you have early calls that you are missing by not having the Contact Center open) and 18:00 (to see if there is a late surge of calls).

   Figure 126: Add Weekly Schedule page – example schedule shows how User Mary Smith configured her Weekly Schedule.



Figure 126: Add Weekly Schedule page – example schedule

Mary Smith selected the Answered Calls by Skillset, Abandoned Call by Skillset, Abandoned CLID/DNIS, and Call Average by Skillset reports to be printed at 08:30 on Mondays.

Her schedule is called **WeeklyCalls**. The reports start generating at 08:30 on the Canon iR5000-6000 PCL5e printer. The reports cover the period from midnight to midnight for each day.

7. Click **Submit** to save your Weekly Schedule. The Weekly Schedules – Skillsets page shown in Figure 127: Weekly Schedules - Skillsets appears.

Weekly Schedules Skillsets

The Weekly Schedule - Skillsets page allows you to select which Skillsets you wish to include in the generated reports that the Weekly Schedule produces.



Figure 127: Weekly Schedules - Skillsets

- For information about using Skillset selection lists, see page 141.
- For information about using Favorites, see page 141.

In the example shown in Figure 127: Weekly Schedules - Skillsets, User Mary Smith used her Skill1&3 Favorite to select the Development and Training Skillsets.

To save your Weekly Schedule Skillsets selections, click **Submit**. The Your Weekly Schedules page appears.

To leave the Weekly Schedule – Skillsets page without saving any changes, click **Cancel**. The Your Weekly Schedules page appears.

Saving Your Weekly Schedule

To save your Weekly Schedule, click **Submit**. The Your Weekly Schedules page shown in Figure 128: Your Weekly Schedule page with a Print Schedule in the list appears. The page shows the schedule you created. In the example, the schedule name is Weekly Calls.

To leave the Add Weekly Schedule page without saving any changes, click **Cancel**. You are prompted to confirm that you do not wish to save your changes. After you confirm the deletion, the Your Weekly Schedules page appears. See Figure 123: Your Weekly Schedules page.

> **Note**: If you include the Agent Audit by Agent, Agent Profile by Agent, Agent Average by Agent, Agent Activity by Agent, Activity Code by Skillset, Activity Code by Agent, or the Activity Code by Pegs Reports in your Print Schedule, you are prompted for the Agents and/or the Activity Codes you wish to include with these Reports. These steps are described on pages 172 (Agent Reports), 172 (Activity Code by Skillset), 172 (Activity Code by Agents) and 172 (Activity Code by Pegs).



Figure 128: Your Weekly Schedule page with a Print Schedule in the list

Note that each Schedule can be identified by the Schedule Name that was provided earlier when the Schedule was created.

Deactivate

Click **Deactivate** to disable the Print Schedule so that the schedule no longer prints when the schedule is due to run. When a schedule is disabled, the Deactivate button changes from Deactivate to Activate and a red cross replaces the green check mark, similar to the following illustration.



Activate

Click **Activate** to enable the Print Schedule so that the schedule prints when the schedule is due to run. When a schedule is enabled, the Activate button changes from Activate to Deactivate and a green check replaces the red cross, similar to the following illustration.



Edit

Click **Edit** to view the Edit Weekly Schedule page, shown in Figure 129: Edit Weekly Schedule page.



Figure 129: Edit Weekly Schedule page

This page is set up exactly like the Add Weekly Schedule page, except the fields and check boxes are populated with the settings of the Schedule you are editing. In the example, you are editing the Weekly Calls schedule. Make any necessary changes and click **Submit**. The Your Weekly Schedules page shown in Figure 123: Your Weekly Schedules page appears.

To leave the Edit Weekly Schedule page without saving any changes, click **Cancel**. The Your Weekly Schedules page shown in Figure 123: Your Weekly Schedules page appears.

Delete

Click **Delete** to remove the Schedule from the system and remove its listing from the Your Weekly Schedules page.

You are prompted to confirm the deletion. When you confirm the deletion, the Your Weekly Schedules page shown in Figure 123: Your Weekly Schedules page appears.

Monthly Schedules

On the Print Schedules page shown in Figure 115: Reports and Schedules page, select **Monthly Schedules** to view the Your Monthly Schedules page. See Figure 130: Your Monthly Schedules page. Initially, the page does not show any schedules.

The Add Monthly Schedule page allows you to specify which reports you wish to include in the Schedule and when to print the scheduled reports.

You can also specify which period of the day the reports contain. You must specify a name for your Schedule and the printer on which you wish to generate the reports.



Figure 130: Your Monthly Schedules page

Follow the steps in this section to add a Monthly Schedule:

1. Click **Add**. The Add Monthly Schedules page shown in Figure 131: Add Monthly Schedule Page appears.



Figure 131: Add Monthly Schedule Page

2. To set a name for your Schedule, enter the name in the **Schedule Name** field. This name helps you identify and distinguish between the different Schedules you create.

3. To select a report to include in the Schedule, select the check box beside the report name. You can select multiple reports.

4. To specify the printer on which the reports are generated, select a printer from the **Select printer** list. The list includes all the printers that are accessible from the Web Host PC. (The reports are generated from the databases held in the Web Host PC.)

5. The reports are generated for a calendar month. You must specify the time you wish to have the Monthly Schedule reports generated. They are generated on the first day of each Month, at the specified time.

In the **Report Period Start Time** and **Report Period End Time** lists, specify the period in each day for which the reports are generated. For example, if your Contact Center has a working day that starts at 08:30 and finishes at 17:30, you may wish to specify the Start Time as 08:00 (to see if you have early calls that you are missing by not having the Contact Center open) and 18:00 (to see if there is a late surge of calls).

Figure 132: Add Monthly Schedule page with example schedule shows an example Monthly Schedule that User Mary Smith configured.



Figure 132: Add Monthly Schedule page with example schedule

Mary Smith selected the Answered Calls by Skillset, Abandoned Calls by Skillset, Abandoned CLID/DNIS, and Call Average by Skillset reports to be printed at 08:30 (on the first day of each new month).

Her schedule is called **MonthlyCalls**. The reports start to generate at 08:30 on the Cannon iR5000-6000 PCL5e printer. The reports cover the period from midnight to midnight for each day.

6. To save your Monthly Schedule click **Submit**. The Monthly Schedules – Skillsets page, shown in Figure 133: Monthly Schedule - Skillsets page appears.

   To leave the Add Monthly Schedule page without saving any changes, click **Cancel**. The Your Monthly Schedules page shown in Figure 130: Your Monthly Schedules page appears.

Monthly Schedule Skillsets

The Monthly Schedule - Skillsets page allows you to select which Skillsets you wish to include in the generated reports that the Monthly Schedule produces.



Figure 133: Monthly Schedule - Skillsets page

- For information about using Skillset selection lists, see page 141.
- For information about using Favorites, see page 141.

In the example shown in Figure 133: Monthly Schedule - Skillsets page, User Mary Smith used her Skill1&3 Favorite to select the Development and Training Skillsets.

Note: If you include the Agent Audit by Agent, Agent Profile by Agent, Agent Average by Agent, Agent Activity by Agent, Activity Code by Skillset, Activity Code by Agent, or the Activity Code by Pegs Reports in your Print Schedule, you are prompted for the Agents and/or the Activity Codes you wish to have included within these Reports. These steps are described on pages 172 (Agent Reports), 172 (Activity Code by Skillset), 172 (Activity Code by Agents) and 172 (Activity Code by Pegs).

To save your Monthly Schedule Skillsets, click **Submit**. The Your Monthly Schedules page shown in Figure 134: Your Monthly Schedules page with a Print Schedule in the list appears.

To leave the Monthly Schedule – Skillsets page without saving any changes, click **Cancel**. The Your Monthly Schedules page appears, as shown in Figure 130: Your Monthly Schedules page.

Saving your Monthly Schedule

To save your Monthly Schedule, click **Submit**. The Your Monthly Schedules page shown in Figure 134: Your Monthly Schedules page with a Print Schedule in the list appears. The page shows the schedule you created. In the example, the schedule name is Monthly Calls.



Figure 134: Your Monthly Schedules page with a Print Schedule in the list

Note: Each Schedule can be identified by the Schedule Name that was provided earlier when the Schedule was created.

Deactivate

Click **Deactivate** to disable the Print Schedule so that the schedule no longer prints when the schedule is due to run. When a schedule is disabled, the button changes from Deactivate to Activate, and a red cross replaces the green check mark, similar to the following illustration.



Activate

Click **Activate** to enable the Print Schedule so that the schedule prints when the schedule is due to run. When a schedule is enabled, the button changes from Activated to Deactivate, and a green check mark replaces the red cross, similar to the following illustration.



Edit

Click **Edit** to view the Edit monthly Schedule page, shown in Figure 135: Edit Monthly Schedule page.



Figure 135: Edit Monthly Schedule page

This page is set up exactly like the Add Monthly Schedule page, except the fields and check boxes are populated with the settings of the Schedule you are editing. In the example, you are editing the Monthly Calls schedule. Make any necessary changes and click **Submit**. The Your Monthly Schedules page appears. See Figure 130: Your Monthly Schedules page.

To leave the Edit Monthly Schedule page without saving any changes, click **Cancel**. The Your Monthly Schedules page appears. See Figure 130: Your Monthly Schedules page.

Delete

Click **Delete** to remove the Schedule from the system and to remove its listing from the Your Monthly Schedules page.

You are prompted to confirm the deletion. After you confirm the deletion, the Your Monthly Schedules page appears. See Figure 130: Your Monthly Schedules page.

Reports 6

Reports Introduction

General

Nortel Reporting for Contact Center provides a set of flexible and easy-to-understand reports. The reports contain information about the call traffic in and out of your Contact Center and about the activities of your Contact Center Agents.

Reports Explained

Detailed information on the Reports within Reporting for Contact Center can be found in the *Reporting for Contact Center – Reports Explained* (NN40010-626) guide (installed along with this guide on the Web Host PC). This guide details how to use the report viewer, the terms used within Reporting for Contact Center reports, what statistics and formulas are used to calculate each field in the reports (where applicable) and frequently asked questions.

Using the Reports

From the Main Menu shown in Figure 72: User Main Menu page, select **Reports and Schedules** to view the Reports and Schedules page, see Figure 136: Reports and Schedules page.



Figure 136: Reports and Schedules page

Under Report Names each report is grouped according to its type, these are in order:

- Agents: reports related to Agent activity and traffic
- Calls: reports related to calls
- Activity Codes: reports related to activity codes
- Miscellaneous: all other reports, such as the System Configuration report
- Single only reports, reports that can only be generated on their own.

Generating reports

Perform the following steps to obtain a report:

1. From the **Report Names** list of reports, select the appropriate check box for each report you wish to generate.

   Note: Most reports require selecting Skillsets, Agents, Activity Codes, or any combination of these. The only reports that do not require these selections are Help Request by Supervisor, Unanswered Help Request by Agent, and System Configuration. For information about selecting Skillsets, refer to Selecting Skillsets. For information about selecting Agents, refer to Selecting Agents. For information about selecting Activity Codes, refer to Selecting Activity Codes.

2. Next to the **From Date** and **To Date** fields click the calendar icon and specify a date. See Figure 137: Selecting a Date Range. A maximum date range of one year can be selected. Use the arrows buttons, such as **<<Year**, to change the year and month of the calendar.



Figure 137: Selecting a Date Range

3. Use the **From Time** and **To Time** fields to specify the time range for the report. Click each field and enter the time, in the 24-hour format. For example, enter 08:00 for 8:00 a.m. and 14:00 for 2:00 p.m.
4. To view your reports on screen, refer to View a report on screen on page 164. To send the reports directly to a printer, refer to Send a report directly to the printer on page 164.
5. To reset all the fields back to the default settings, click **Reset**.

View a report on screen

To view reports on screen, click **View** in the Reports and Schedules page, see Figure 136: Reports and Schedules page. After you select skillsets, agents and activity codes (where applicable) each report will open in its own window.

Send a report directly to the printer

Perform the following steps to send reports directly to a printer:

1. Select a printer from the **Send to Printer** list.

Note: You can only print to printers that are configured and connected to the Web Host PC.

2. Enter a print delay time in the **Print Delay** field, in the format hh:mm.

   The print delay time can be up to 24 hours in the future. For example, if the current time is 12:30 and you specify **3:30** in the **Print Delay** field, your reports will print at 16:00 that day. If you specify **23:00**, your reports will print at 11:30 the following day.

   Note: 23:59 is the maximum print delay time you can enter in the **Print Delay** field and 00:01 is the minimum.

3. Click **Print** to send the report to the selected printer.

   The Print Status page will open, as shown in Figure 138: Print Status page. This page lists all the *ad hoc* report print requests, the date and time they are due to be printed and a link, called **Cancel Print**, to cancel each report print job. For more information on cancelling report print jobs, refer to Cancel reports to be printed on page 167.

   If there are more reports than can be displayed in this window a scroll bar will appear on the right hand side. Use this to scroll through all reports waiting to print.


Nortel Reporting for Contact Center - Windows Internet Explorer
http://30.30.30.152/rcc/report_pages/report_print.asp?{727dd411-9c57-b6f9-920e-0c86db4c
NORTEL
The selected report(s) will be printed at Fri Jun 15 15:04:58
Answered Calls by Skillset 2007/06/15 15:05 Cancel Print
Help Request by Supervisor 2007/06/15 15:05 Cancel Print
Agent Average by Agent 2007/06/15 15:05 Cancel Print
Agent Activity by Agent 2007/06/15 15:05 Cancel Print
System Configuration 2007/06/15 15:05 Cancel Print
Call Breakdown by Agent 2007/06/15 15:05 Cancel Print
Cancel All
Warning: Your reports will still print if you close this window.
If you refesh this screen your reports will print twice.
Done
Internet
100%

Figure 138: Print Status page

4. If you click on the Close button to close this window, you can re-open the Print Status page to view print jobs by clicking on **View/Cancel print jobs** from the Reports and Schedules page.

Cancel reports to be printed

Perform one of the following to cancel report print jobs before they are due to print:

- From the Print Status page, click **Cancel Print** next to each report print job. To cancel all print jobs, click **Cancel All**; or
- If the Print Status page is already closed, re-open the Print Status page to view all *ad hoc* print requests by clicking on **View/Cancel print jobs** from the Reports and Schedules page.

  Click **Cancel Print** next to each report print job to cancel, or click **Cancel All** to cancel all print jobs.

Selecting Skillsets

If you select to generate any of the following reports, you must choose the Skillsets for which you want the reports generated:

- Agent Capacity by Skillset
- Abandoned Calls by Skillset
- Abandoned CLID/DNIS
- Answered Calls by Skillset
- Answered CLID/DNIS
- Call Average by Skillset
- Call Profile
- Incoming Call by Skillset
- Summary
- Activity Code by Agent
- Activity Code by Pegs
- Activity Code by Skillset

If you select to generate one of the reports in the list, the Select Skillsets page shown in Figure 139: Select Skillsets page appears.



Figure 139: Select Skillsets page

- For information about using Skillset selection lists, see page 141.
- For information about using Favorites, see page 141.

Selecting Agents

If you select to generate any of the following reports, you must choose the Skillsets for which you want the reports generated:

- Agent Activity by Agent
- Agent Audit by Agent
- Agent Average by Agent
- Agent Profile by Agent

The Select Agents page shown in Figure 140: Select Agents or Skillsets page appears.



Figure 140: Select Agents or Skillsets page

Use the following techniques to select items from the Agents and Skillsets lists:

- Click an unselected item name once to select it (it will be highlighted) and remove the highlight from any other currently selected items in the list box.
- Click a selected (highlighted) item once to unselect it. Note that if other items are selected and you click an item, you unselect all the other items except the item you clicked in the same list box.
- To select multiple items, press **Ctrl** and select multiple items in the list box.
- To select a range of items, click an item at the beginning (or end) of the range, press the Shift key, and click the item at the end (or beginning) of the range.

You can also click **Select All** to select all the items in the list box above at once.

Although you can select Skillsets on this page when you submit the page it is the Agents you've selected that are used to generate your reports. By selecting a Skillset and clicking the > arrow box you will automatically highlight all agents who have logged into that Skillset, by selecting

an Agent and clicking the < arrow box you will automatically highlight any skillsets that the agent has logged into.

In cases where you want to view only the agents who logged into a particular skillset you can use the technique above.

Selecting Activity Codes

If you select to generate any of the following reports, you must choose the Activity Codes for which you want the reports generated:

- Activity Code by Skillset
- Activity Code by Agent

The Select Activity Codes page shown in Figure 141: Select Activity Codes page appears.



Figure 141: Select Activity Codes page

Use the following techniques to select Activity Codes from the Activity Codes list:

- Click an unselected Activity Code once to select it (it will be highlighted) and remove the highlight from any other currently selected Activity Code.
- Click a selected (highlighted) Activity Code once to unselect it.

  Note: If any other Activity Codes are selected and you click an Activity Code, you unselect all the other Activity Codes except the Activity Code you clicked.
- To select multiple Activity Codes, press **Ctrl** while you select multiple Activity Codes.
- To select a range of Activity Codes, click an Activity Code at the beginning (or end) of the range, hold down the Shift key, and click the Activity Code at the end (or beginning) of the range.

You can also click **Select All** to select all the Activity Codes at once.

Get Latest Contact Center Data item

From the **Reports** menu, choose the **Get Latest Contact Center Data** item, see Figure 136: Reports and Schedules page (page 162), to request the most recent report data from the Contact Center.

For example, if you specified that Nortel Reporting for Contact Center should poll the Contact Center every 30 minutes for report data, clicking Get Latest Contact Center Data ensures that the most recent data is received from the Contact Center before the reports are generated. Any Contact Center activity that has occurred since the last Report Data update is included in the reports.

When you click **Get Latest Contact Center Data**, the screen shown in Figure 142: Get Latest Contact Center Data appears. This screen shows the number of seconds remaining until the latest data is obtained from the Contact Center.

Nortel Reporting for Contact Center - Windows Internet E...
Nortel Reporting for Contact Center -
NORTEL
Get Latest Contact Center Data.... 7

Figure 142: Get Latest Contact Center Data

To reset the timer, click **Get Latest Contact Center Data** again while the screen is open. By having the data request timer reset in the same screen prevents the User from making multiple repeated and rapid data requests from the Contact Center.

Glossary 9

Abandoned Calls..... Abandoned Calls are calls that ring in to the system and the incoming caller clears down the call because they do not wish to wait any longer before they are answered. These calls have not been handled by humans or by voice mail.

Abandon Time Bins... A series of six time steps used in the statistical analysis of Abandoned Calls. Nortel Reporting for Contact Center will provide statistical reports on the percentage of incoming calls abandoned within each of the periods specified in the Abandoned Time Bins. A seventh period is also used in the reports, which gathers information on all calls which abandoned after the period specified by the sixth Abandoned Time Bin.

Administrator..... A Nortel Reporting for Contact Center User who has been awarded Administration rights. These Users can configure core elements of Nortel Reporting for Contact Center that regular Users can not, and they can perform such actions as creating other Users.

Alarm Threshold..... Alarms may be set to trigger an alert on the wallboards, to inform your Agents of some event or circumstance. The value that a parameter must reach, match or exceed to trigger an Alarm is the Alarm Threshold.

All Calls Held ..... If an Agent has placed all of their calls on hold, so that they have no active calls, they will be shown in pink in the Real Time screens.

Answered Time Bins.. A series of six time steps used in the statistical analysis of Answered Calls. Nortel Reporting for Contact Center will provide statistical reports on the percentage of incoming calls answered within each of the periods specified in the Answered Time Bins. A seventh period is also used in the reports, which gathers information on all calls that were answered after the period specified by the sixth Answered Time Bin.

Available State..... The Agent is ready to take Incoming calls. The Available State is shown as blue in the Real Time screens.

Break Time..... The period allocated to Agents following clear down of an Incoming Contact Center Call (also known as Wrap Up and Post Call Completion). Break Time is displayed in the Real Time screens as green.

Calls Answered..... 'Answered' means the Call was not abandoned, and it did not require the involvement of another Skillset in the handling of the call.

Calls Handled In Another Skillset ..... Calls that have left a Skillset and entered another Skillset because of an Overflow Rule or any other Routing Condition or Step. The fate of these calls is then recorded in the reports for the Skillset they have moved to – not in the Skillset they leave.

Calls Presented..... The counts all of the calls that were presented to a Skillset, both Direct (a 'regular Contact Center call' delivered straight into the Skillset,) and Indirect, which means the call arrived in the Skillset in some other way.

Direct Call..... From the point of view of any given Skillset, Direct Calls are calls that were presented directly to that Skillset. That is, the incoming caller was handled by the Call Routing and was presented by the Call Routing directly to the Skillset in question.

Incoming State ..... The Agent is engaged on an Incoming Contact Center Call, either a PSTN or a Multimedia call. The Incoming State is shown as light green for a PSTN call, or bright green for a Multimedia call in the Real Time screens. If an Agent has been on an Incoming Call in excess of the Incoming Call Duration Threshold their timer will be displayed against a red background.

Indirect Call ..... From the point of view of any given Skillset, Indirect Calls arrived in the Skillset after being handled by the Call Routing or Agents of another Skillset. For example, they may have overflowing from another Skillset or may have been manually transferred to the Skillset queue by an Agent from another Skillset. Any way a Call can arrive into a Skillset other than being a regular Contact Center Call presented directly to the Skillset (as described above) is counted as an Indirect Call. Whether the call overflowed to the Skillset in question, or was moved to the Skillset by the Move to Queue Call Routing step, or whether it was manually transferred to the Skillset Control DN, it is counted as an Indirect Call.

Multimedia Call ..... A call generated and conducted through the use of Nortel Multimedia Contact Center. This call would be initiated by a caller clicking a button on a Web page.

Non-Contact Center Call State ..... Dark green is used for non-Contact Center calls.

Not Available State…. Agents who are Not Available may enter this state through actions like F981 voice mail, lifting the receiver (while not answering a call) and any other action that removes their ability to receive a call.

Not Ready State ..... Either the Agent has invoked the Make Not Ready feature (Feature 908) to indicate they are not available to take calls or the Contact Center has placed them in the Not Ready state because a call was unanswered at their handset or the Agent is active on an internal call. The Not Ready State is shown as dark grey in the Real Time ccreens. If an Agent has been Not Ready in excess of the Not Ready Duration Threshold their timer will be displayed against a red background.

Outgoing State ..... The Agent is engaged on an Outgoing Call. The Outgoing State is shown as yellow in the Real Time screens. If an Agent has been on an Outgoing Call in excess of the Outgoing Call Duration Threshold their timer will be displayed against a red background.

PSTN Call ..... Public Switched Telephone Network Call – a 'regular' voice call.

Real Time..... Information is available that displays the current states of Skillset Calls and Agents. This information is refreshed approximately every 3 seconds. These displays are called the Real Time screens. Information can also be displayed on hardware and software TCP/IP enabled wallboards, to provide Real Time information to the Contact Center Agents.

Ringing..... Agents who have calls currently ringing on their handset.

Service Level ..... The Service Level is a figure that is used to represent the level of service provided to incoming callers, based upon Contact Center response times. It is calculated as follows:

```
Presented    = Total Number of Direct Call
               transactions Presented to the Skillset
Abandoned    = Calls which Abandoned
>Secondary   = Calls transactions answered after the
               Secondary Alert

Service Level % = Presented – Abandoned – >Secondary  x 100
                                  Presented
```

Stat Time Bins..... A collective term for the Abandoned Time Bins and the Answered Time Bins.

Supervisor Monitoring If a Supervisor is monitoring an Agent the Supervisor is displayed in the Agent Detail Real Time screen with an orange background and the Status column displaying **Monitoring**.

TCP/IP..... Transmission Control Protocol/Internet Protocol: a protocol developed by the US Department of Defense for communications between computers. It has become the *de facto* standard for data transmission over networks, including the Internet. TCP and IP are transport and address protocols; TCP is used to establish a connection for data transmission, and IP defines the method for sending the data in packets.

Title..... A string of text displayed on the top line of a wallboard. This restricts the wallboard to being able to display 3 parameters only.

User..... A User is a person who has been allocated a Username and Password to allow them to use Nortel Reporting for Contact Center. Users can configure some elements of their usage of Nortel Reporting for Contact Center, but they do not have the same scope for configuration as an Administrator.

Unstaffed Calls..... Calls that were presented to the Skillset when there were no Agents logged in to handle those calls.

Wallboard..... This is a device that is used to display Contact Center statistics and messages to the Agents and other Contact Center staff. Nortel Reporting for Contact Center TCP/IP enabled hardware **Wallboards** and SoftBoard's from the *ip***View** range of wallboards.

References 10

1 *Contact Center Set Up and Operation Guide* (NN40040-301)
2 *Keycode Installation Guide* (NN40010-301)
3 *ipView Software Wallboard Setup and Operation Guide* (NN40010-500)
4 *Reporting for Contact Center – Reports Explained* (NN40010-626)
5 *Reporting for Contact Center Troubleshooting and Maintenance Guide* (NN40020-403)
6 *Upgrading from Call Center Reporting to Reporting for Contact Center* (NN40010-400)

Index

A

Abandon Time Bins, 131, 173
Abandoned, 86, 88, 91, 102, 131, 133, 140, 149, 156, 167, 173, 175
Abandoned Call, 131, 140, 149, 156, 167, 173
Abandoned Calls by Skillset report, 140, 156, 167
Abandoned CLID/DNIS report, 140, 149, 156, 167
Abandoned Time Bins, 131, 133, 173, 175
Activity Code, 135, 143, 151, 158, 163, 167, 170, 171
Activity Code by Agent report, 135, 143, 151, 158, 167, 170
Activity Code by Pegs report, 135, 143, 151, 158, 167
Activity Code by Skillset report, 135, 143, 151, 158, 167, 170
Add Alarm, 117, 118
Add Message, 113, 114, 115, 116
Add User, 68, 70, 71, 72, 102
Add Wallboard, 106, 107, 108, 110
Administration Menu, 64, 65, 67, 72, 80
Administrator, 11, 13, 14, 29, 30, 34, 57, 60, 61, 64, 65, 66, 68, 69, 70, 80, 81, 83, 102, 104, 108, 129, 132, 173, 176
Agent, 67, 83, 88, 89, 92, 93, 94, 95, 96, 97, 98, 99, 100, 101, 107, 135, 143, 151, 158, 163, 167, 168, 169, 170, 173, 174, 175
Agent Activity by Agent report, 135, 143, 151, 158, 168
Agent Alarms, 83, 97, 98, 99, 100, 101
Agent Audit by Agent report, 135, 143, 151, 158, 168
Agent Average by Agent report, 135, 143, 151, 158, 168
Agent Capacity by Skillset report, 167
Agent Detail, 92, 97, 175
Agent Profile by Agent report, 135, 143, 151, 158, 168
Alarm Messages, 103
Alarm Periods, 119, 120, 122
Alarm Thresholds, 104
Answer Time Bins, 131
Answered Call, 97, 104, 131, 140, 149, 156, 167, 173
Answered Calls by Skillset report, 140, 149, 156, 167
Answered CLID/DNIS report, 167
Assigned Skillsets, 14, 73, 74, 75
Available, 89, 93, 96, 100, 102, 173, 174

B

BCM 4.0, 61
BCM50 3.0, 15, 20, 61
Brazilian Portuguese, 13
Break Time, 89, 93, 173
Business Communications Manager, 13, 26, 30
Buzzer, 108

C

Call Average by Skillset report, 149, 156, 167
Call Detail, 88, 90
Call Profile report, 167
Call Routing, 174
CallPilot, 13, 47, 61, 74
Canadian French, 13
Company Details, 64, 79, 80
Contact Center, 13, 15, 17, 20, 26, 29, 30, 47, 59, 60, 61, 62, 63, 64, 67, 74, 77, 86, 90, 91, 93, 95, 98, 104, 139, 148, 156, 171, 172, 175
Contact Center Connection, 13, 59, 60, 61, 64, 102
Contact Center Reporting Server, 47, 61
Control key, Ctrl, 57, 75, 81, 141, 169, 171
Control Panel, 17, 20, 21, 24, 26, 30, 55, 56

D

Daily Schedules, 135, 136, 137, 138, 139, 140, 141, 143, 144, 145, 146
Danish, 13
Direct Call, 88, 174, 175
Dutch, 13

E

Edit Parameters, 110, 111
Edit User, 71
Edit Wallboard, 109, 110
Element Manager, 30

F

Favorites, 14, 57, 81, 85, 99, 129, 141, 142, 150, 157, 168
French, 13

G

German, 13

H

Help Request by Supervisor report, 163

I

IBM, 15
Incoming Call by Skillset report, 167
Indirect Call, 174
Installation, 11, 17, 20, 22, 23, 24, 29, 30, 43, 44, 45, 46, 47, 48, 49, 177
InstallShield, 17, 18, 21, 32, 34, 37, 38, 39, 40, 41, 43
Instant Messages, 104, 105, 128, 129, 130
Intel, 15
Internet Explorer, 13, 15, 16, 17, 18, 19, 24, 30, 57, 81
Internet Information Services, 16, 20, 21, 22, 23, 24, 25, 26, 27, 28, 47, 63
Introduction, 11, 13, 17, 161
IP Address, 30, 57, 61, 81, 107
ipView Softboard, 26, 102, 103, 107, 176
Italian, 13

J

Java Runtime Environment, 18, 46, 77, 85

L

Language Support, 13
Latin American Spanish, 13
License Agreement, 35, 40, 41
Log on, 81
Logging Menu, 78
Login, 30, 34, 53, 57, 58, 81, 116, 127
Longest Waiting Time, 87, 92

M

Maintenance, 20, 63, 64, 76, 177
Microprocessor, 15
Microsoft, 14, 16, 18, 20, 21, 26, 34, 36, 37, 38, 46, 63
Microsoft SQL Server, 14, 18, 37
Minimum PC Requirements, 15
Monitoring, 95, 175
Monthly Schedules, 135, 153, 154, 155, 156, 157, 158, 159, 160
Mouse, 16
Multimedia Call, 90, 100, 174

N

Network Name, 107
Nortel Call Center Reporting, 17, 177
Nortel Multimedia Contact Center, 95, 174
Nortel Networks Call Center Reporting, 17
Nortel Reporting for Contact Center, 11, 13, 14, 15, 16, 17, 18, 20, 22, 26, 29, 30, 31, 32, 33, 34, 37, 40, 42, 43, 44, 57, 61, 62, 63, 65, 66, 67, 68, 69, 70, 74, 76, 77, 78, 79, 80, 81, 83, 89, 97, 98, 99, 102, 103, 104, 107, 108, 120, 131, 133, 135, 142, 161, 171, 173, 176, 177
North American English, 13
Norwegian, 13
Not Available, 89, 96, 174
Not Ready, 89, 96, 100, 102, 104, 108, 115, 119, 121, 175

O

On Contact Center Calls, 89
On Internal Calls, 90
On Non-Contact Center Calls, 90
On Outgoing Calls, 90
Operating System, 16
Overflow, 86, 91, 174

P

Parameters, 110, 111, 120
Password, 58, 59, 71, 72, 81, 82, 176
Port Number, 26, 61, 77, 107
Primary Alert, 86, 91
Print Schedules, 49, 53, 56, 83, 135, 146, 153
Printer, 164

R

Real Time screens, 13, 14, 15, 17, 26, 61, 62, 67, 72, 78, 80, 83, 84, 85, 87, 88, 89, 90, 92, 93, 94, 97, 98, 173, 174, 175
Report Viewer, 37, 38
Reset Password, 71, 72
Ringing, 89, 96, 175

S

Scheduled Messages, 104
Scrolling Messages, 102, 103
Secondary Alert, 86, 88, 91, 175
Service Level, 87, 88, 92, 102, 105, 119, 175
Skillset Assignment, 65, 69, 72, 73, 75
Skillset selection, 14, 85, 99, 107, 129, 131, 132, 134, 150, 157, 168
Spanish, 13
Statistical Data, 14, 16
Summary Messages, 102, 104
Supervisor, 95, 163, 175
Supervisor Monitor, 175
SVGA, 15
Swedish, 13
System Admin Settings, 65, 66
System Administration Menu, 65, 67, 72
System Status, 76, 77

T

TCP/IP, 15, 29, 30, 175, 176
Time Bins, 83, 131, 132, 133, 134, 173, 175
Time Bins Setup, 83, 131
Title, 108, 176
Troubleshooting, 20, 63, 177

U

Unanswered Help Request by Agent report, 163
United Kingdom English, 13
Unread Skillset Messages, 87
Upgrading, 17, 18, 177
URL, 57, 81
User, 11, 13, 14, 15, 17, 34, 35, 62, 65, 66, 67, 68, 69, 70, 71, 72, 73, 74, 75, 80, 81, 82, 83, 84, 87, 98, 99, 102, 103, 104, 105, 106, 108, 115, 116, 120, 126, 128, 129, 131, 132, 135, 139, 148, 150, 156, 157, 161, 172, 173, 176
User Admin, 65, 66, 67, 69, 70, 71, 72

V

Voice (PSTN) Call, 90, 94, 174, 175

W

Wallboard, 62, 69, 83, 102, 104, 105, 106, 107, 108, 109, 110, 111, 112, 117, 118, 123, 125, 128, 176
Wallboard Assignment, 69, 105, 106

Web Host, 13, 15, 17, 18, 20, 23, 25, 26, 29, 32, 44, 53, 54, 57, 60, 61, 63, 77, 81, 135, 139, 148, 155, 161, 165
Web Host PC, 13, 15, 17, 18, 20, 23, 25, 26, 29, 32, 44, 53, 54, 57, 60, 61, 63, 77, 81, 135, 139, 148, 155, 161, 165
Web page, 68, 70, 174
Weekly Schedules, 135, 146, 147, 148, 149, 150, 151, 152, 153
Windows, 16, 17, 18, 21, 22, 23, 24, 26, 27, 28, 29, 30, 47, 49, 52, 53, 54, 55, 56, 79
Windows 2000, 16, 30
Windows 2003, 16, 148
Windows 95, 98, 123, 124, 147
Windows Networking Component, 29
Windows Vista, 16, 26, 29
Windows XP, 16, 30, 79
With All Calls Held, 90

X

XML, 76